

OWNER'S MANUAL LED LCD MONITOR

Please read this manual carefully before operating your set and retain it for future reference.

LED LCD MONITOR MODEL

22M45HQ

23M45HQ

24M45HQ

27M45HQ

CONTENTS

3 ASSEMBLING AND PREPAR-ING

- 3 Unpacking
- 4 Parts and buttons
- 5 Moving and Lifting the Monitor
- 6 Setting up the Monitor set
- 6 Attaching the Stand Base
- 7 Detaching the Stand Base
- 8 Mounting on a table
- 8 Using the cable holder
- 10 Mounting on a wall

11 USING THE MONITOR SET

- 11 Connecting to a PC
- 11 D-SUB connection
- 11 HDMI connection
- 12 Connecting to AV Devices
- 12 HDMI connection
- 13 Headphone port connection

14 CUSTOMIZING SETTINGS

- 15 Customizing Settings
- 15 Menu Settings
- 16 -Picture
- 17 -Color
- 18 -Display
- 18 -Audio
- 19 -Others
- 20 READER Setting
- 21 FUNC. Setting
- 21 -SUPER ENERGY SAVING

- 22 -Picture Mode
- 23 DUAL DISPLAY
- 23 -DUAL WEB

24 TROUBLESHOOTING

26 SPECIFICATIONS

- 26 22M45HQ
- 27 23M45HQ
- 28 24M45HQ
- 29 27M45HQ
- 30 Preset Modes (Resolution)
- 30 Indicator


31 PROPER POSTURE

31 Proper posture for using the Monitor set.

ASSEMBLING AND PREPARING

Unpacking

Check your product box for the following items. If there are any missing accessories, contact the local dealer where you purchased your product. The illustrations in this manual may differ from the actual product and accessories.





CAUTION


- Do not use any unapproved accessories to ensure the safety and product life span.
- Any damages or injuries by using unapproved accessories are not covered by the warranty.



NOTE -

- The accessories supplied with your product may vary depending on the model.
- Product specifications or contents in this manual may be changed without prior notice due to upgrade
 of product functions.


Parts and buttons



Moving and Lifting the Monitor

When moving or lifting the monitor, follow these instructions to prevent the monitor from being scratched or damaged and to ensure safe transportation regardless of its shape or size.

- It is advisable to place the monitor in the original box or packing material before attempting to move it.
- Before moving or lifting the monitor, disconnect the power cord and all cables.
- Hold the top and bottom of the monitor frame firmly. Do not hold the panel itself.



 When holding the monitor, the screen should face away from you to prevent it being scratched.



- When moving the monitor, avoid any strong shock or vibrations to the product.
- When moving the monitor, keep it upright, never turn the monitor on its side or tilt it sideways.



CAUTION

 As far as possible, avoid touching the monitor screen. This may result in damage to the screen or some of the pixels used to create images.



Setting up the Monitor set

Attaching the Stand Base

1 Place the Monitor set with the screen side down on a flat and cushioned surface.




CAUTION

Lay a foam mat or soft protective cloth on the surface to protect the screen from damage.


2 22M45HQ/23M45HQ/24M45HQ

- 1 Attach the **Stand Body** to the monitor set.
- 2 Attach the Stand Base.
- 3 Tighten the screw to the right.




27M45HQ

- 1 Attach the Stand Body to the monitor set.
- Use two screws to fix the Stand Body and monitor set.
- 3 Attach the Stand Base.
- 4 Tighten the screw to the right .




Detaching the Stand Base

- 1 Place the Monitor set with the screen side down on a flat and cushioned surface.
- 2 22M45HQ/23M45HQ/24M45HQ
 - 1 Pull out the **Stand Body** and **Stand Base** from the monitor set.
 - 2 Turn the screw to the left.
 - 3 Pull out the Stand Base.



27M45HQ

- 1 Turn the screw to the left.
- 2 Pull out the Stand Base from the Stand Body.
- Remove two screws and pull out the **Stand Body** from the monitor set.






CAUTION

- This illustration depicts the general model of connection. Your monitor may differ from the items shown in the picture.
- Do not carry the product upside down holding only the stand base. The product may fall and get damaged or injure your foot.


Mounting on a table


1 Lift and tilt the Monitor set into its upright position on a table.

Leave a 10 cm (minimum) space from the wall for proper ventilation.



2 Connect the AC-DC Adapter and Power Cord to a wall outlet.






3 Press ϕ (Power) button on the bottom switch panel to turn the power on.




CAUTION

Unplug the power cord before moving the Monitor to another location. Otherwise electric shock may occur.


Using the cable holder






WARNING -

When you adjust the angle, do not hold the bottom of the Monitor set frame as shown on the following illustration, as may injure your fingers.



Do not touch or press the screen when adjusting the angle of the monitor.



Do not hold this set like below picture. Monitor screen can detach from stand base and injure your body.




22M45HQ/23M45HQ/24M45HQ



NOTE

Tilt from +20 to -3 degrees up or down to adjust the angle of the Monitor set to suit your view.




27M45HQ



NOTE -


Tilt from +20 to -5 degrees up or down to adjust the angle of the Monitor set to suit your view.



Using the Kensington security system

The Kensington security system connector is located at the back of the Monitor set. For more information of installation and using, refer to the manual supplied with the Kensington security system or visit http://www.kensington.com.

Connect the Kensington security system cable between the Monitor set and a table.






NOTE -

The Kensington security system is optional. You can obtain it from most electronics stores.

Mounting on a wall

For proper ventilation, allow a clearance of 10 cm on each side and from the wall. Detailed instructions are available from your dealer, see the optional Tilt Wall Mounting Bracket Installation and Setup Guide.



If you intend to mount the Monitor set to a wall, attach Wall mounting interface (optional parts) to the back of the set.

When you install the Monitor set using a wall mounting interface (optional parts), attach it carefully so it will not drop.


- 1 Please, Use the screw and wall mount interface in accordance with VESA Standards.
- 2 If you use screw longer than standard, the monitor might be damaged internally.
- 3 If you use improper screw, the product might be damaged and drop from mounted position. In this case, LG Electronics is not responsible for it.
- 4 VESA compatible only with respect to screw mounting interface dimensions and mounting screw specifications.
- 5 Please use VESA standard as below.
- 784.8 mm (30.9 inch) and under
 - * Wall Mount Pad Thickness: 2.6 mm
 - * Screw : Φ 4.0 mm x Pitch 0.7 mm x Length 10 mm
- 787.4 mm (31.0 inch) and above
 - * Please use VESA standard wall mount pad and screws.

Model	22M45HQ 23M45HQ	24M45HQ 27M45HQ
VESA (A x B)	75 x 75	100 x 100
Standard screw	M4	M4
Number of screws	4	4



CAUTION

- Disconnect the power cord first, and then move or install the Monitor set. Otherwise electric shock may occur.
- If you install the Monitor set on a ceiling or slanted wall, it may fall and result in severe injury.
- Use only an authorized LG wall mount and contact the local dealer or qualified personnel.
- Do not over tighten the screws as this may cause damage to the Monitor set and void your warranty.
- Use only screws and wall mounts that meet the VESA standard. Any damages or injuries by misuse or using an improper accessory are not covered by the warranty.
- Screw length from outer surface of back cover should be under 8mm.





NOTE

- Use the screws that are listed on the VESA standard screw specifications.
- The wall mount kit will include an installation manual and necessary parts.
- The wall mount bracket is optional. You can obtain additional accessories from your local dealer.
- The length of screws may differ depending on the wall mount. Be sure to use the proper length.
- For more information, refer to the instructions supplied with the wall mount.


USING THE MONITOR SET

Connecting to a PC

Your Monitor set supports Plug & Play*.
 *Plug & Play: A PC recognizes a connected device that users connect to a PC and turn on, without device configuration or user intervention.


D-SUB connection

Transmits analog video from your PC to the Monitor set. Connect the PC and the Monitor set with the supplied D-sub 15 pin signal cable as shown in the following illustrations.





When using a D-Sub signal input cable connector for Macintosh




Mac adapter

For Apple Macintosh use, a separate plug adapter is needed to change the 15 pin high density (3 row) D-SUB VGA connector on the supplied cable to a 15 pin 2 row connector.

HDMI connection

Transmits the digital video and audio signals from your PC to the Monitor set. Connect the PC and the Monitor set with the HDMI cable as shown in the following illustrations.





 If you use HDMI PC, it can cause compatibility problem.

CAUTION

 Connect the signal input cable and tighten it by turning the screws clockwise.



- Do not press the screen with your finger for a long time as this may result in temporary distortion on the screen.
- Avoid displaying a fixed image on the screen for a long period of time to prevent image burn. Use a screensaver if possible.




NOTE -

- When you want to use two PC in our Monitor, please connect the signal cable(D-SUB/ HDMI) respectively in Monitor set.
- If you turn the Monitor set on while it is cold, the screen may flicker. This is normal.
- Some red, green, or blue spots may appear on the screen. This is normal.

Connecting to AV Devices

HDMI connection

Transmits the digital video and audio signals from your AV devices to the monitor. Connect your AV device to the monitor with the HDMI cable as illustrated below.






NOTE

 If you use HDMI PC, it can cause compatibility problem.

Headphone port connection

Use the headphone port to connect a peripheral device to the monitor. Connect as illustrated.



0

NOTE

 For an angle plug earphone, it is difficult connect it with a peripheral device, so use a straight type.





Angle Type

Straight Type




NOTE

 Depending on the audio settings of the PC and external device, headphone and speaker functions may be limited.

Self Image Setting Function

Press the power button on the bottom panel to turn the power on. When monitor power is turned on, the "**Self Image Setting**" Function is executed automatically. (Only supported in Analog Mode)





NOTE

"Self Image Setting" Function.


This function provides the user with optimal display settings. When the user connects the monitor for the first time, this function automatically adjusts the display to optimal settings for individual input signals. (Only supported in Analog Mode)

'AUTO' Function.

When you encounter problems such as blurry screen, blurred letters, screen flicker or tilted screen while using the device or after changing screen resolution, press the AUTO function button to improve resolution. (Only supported in Analog Mode)

CUSTOMIZING SETTINGS

- 1 Press the desired button on the bottom of the Monitor set.
- 2 Change the value of the menu item by pressing the buttons on the bottom of the Monitor set. To return to the upper menu or set other menu items, use the up arrow (1) button.
- 3 Select **EXIT** to leave the OSD menu.



Button	Description			
MENU / L	Accesses the main menus.(See p.15)			
	OSD Locked/OSD Unlocked	This function allow you to lock the current control settings, so that they cannot be inadvertently changed. Press and hold the MENU button for several seconds. Then OSD of "OSD Lock" will appear. After that, user can select lock or unlock by pressing left/right button. If user selects the "Lock" icon by pressing the "OK" button, the message "OSD Locked" will appear. Otherwise, "OSD Unlocked" will appear. After selecting the "Lock", If you want to change to Unlock, you can push the "MENU" button for several seconds. The message "OSD Unlocked" will appear.		
READER/◀	Use this button to enter Reader Mode menu. Its function works to display screen as paper-like picture for Eye comfort.If you want to more information(See p.20).			
FUNC./▶	Use this button to enter SUPER ENERGY SAVING, Picture Mode, DUAL DISPLAY, DUAL WEB menus.(See p.21~23)			
AUTO / ▼	When adjusting your display settings, always press the AUTO button on the MONITOR SETUP OSD. (Only supported in Analog Mode)			
	The best display mode 1920 x 1080			
INPUT / EXIT	You can choose the input signal. When two input signals are connected, you can select the input signal (D-SUB/HDMI) you want. When only one signal is connected, it is automatically detected. The default setting is D-SUB.			
	EXIT	EXIT		
	EXIT the OSD(On Screen	n Display).		
Ů (Power Button)	Turns the power on or off.			
	Power Indicator	The power indicator stays white if the display is running properly (On Mode). If the display is in Sleep Mode, the power indicator blinks white.		

Customizing Settings

Menu Settings

- 1 Press MENU button on the bottom of the Monitor set to display the Menu OSD.
- 2 Set the options by pressing the ◀ or ▶ or ▼ buttons.
- 3 Select the "**Next Menu**" button to enter the more option settings.
- 4 Select **EXIT** to leave the OSD menu.

 To return to the upper menu or set other menu items, use the up arrow (♠) button.



Menu	Analog	HDMI	Description		
Brightness	•	•	To adjust the brightness of the serson		
Contrast	•	•	To adjust the brightness of the screen		
Response Time	•	•	You can set a response time for displayed pictures based on the speed of the screen. For a normal environment, it is recommended that you use 'Off'. For a fast-moving picture, it is recommended that you use 'High'.		
Wide/Original			Wide		
	Sv		Switch to full screen mode according to input image signal.		
	•	•	Original		
			Change the input image signal ratio to original. * This function works only if input resolution is lower than Monitor set ratio (16:9).		
Reset	•	•	Restore all factory default settings. Press the ◀ , ▶ buttons to reset immediately.		


M	lenu > Next Menu	Analog	HDMI	Description
Picture	Sharpness	arpness • To adjust the clearness of the screen		To adjust the clearness of the screen
	Black Level		•	To set offset level
	Over Scan		•	To improve the clarity and stability of the screen
Color	Gamma		_	To quatomize the color of the coroon
	Color Temp	"	•	To customize the color of the screen
Display	Horizontal			To adjust the modition of the course
Vertical	" "		To adjust the position of the screen	
	Clock		•	To improve the clarity and stability of the screen
	Phase	•		
Audio	Volume		•	To adjust the volume
Others	Language		_	
	Power Indicator	-	•	To customize the screen status for a user's operating environment
	Automatic Standby	•	•	CHVIIOHHOR

- Analog: D-SUB(Analog signal) input.
- HDMI: HDMI(Digital signal) input.

Picture

- 1 Press **MENU** button on the bottom of the Monitor set to display the **Menu** OSD.
- 2 Select the "**Next Menu**" button to enter the more option settings.
- 3 Enter to **Picture** by pressing the ▼ button.
- 4 Set the options by pressing the ◀ or ▶ or ▼ buttons.
- 5 Select **EXIT** to leave the OSD menu.

 To return to the upper menu or set other menu items, use the up arrow (1) button.



Menu > Next Menu > Picture	Description		
Sharpness	To adjust the clearness of the screen.		
Black Level	You can set the offset level. If you select 'High', the screen will be bright and if you select 'Low', the screen will be dark.(only for HDMI input) * Offset?As the criteria for video signal, it is the darkest screen the monitor can show.		
Over Scan	To select the range of output image for DTV timing in HDMI input.(only for HDMI input)Recommend overscan function to turn on when connect AV equipment.		

Color

- 1 Press **MENU** button on the bottom of the Monitor set to display the **Menu** OSD.
- 2 Select the "Next Menu" button to enter the more option settings.
- 3 Select **Color** by pressing the ▶ button.
- 4 Enter to **Color** by pressing the ▼ button.
- 5 Set the options by pressing the ◀ or ▶ or ▼ buttons.
- 6 Select **EXIT** to leave the OSD menu.

 To return to the upper menu or set other menu items, use the up arrow (♠) button.



Menu > Next Menu > Color	Description
Gamma	Set your own gamma value. : Gamma 0, Gamma 1, Gamma 2 on the monitor, high gamma values display whitish images and low gamma values display blackish images.
Color Temp	Custom
	 Red:Set your own red color levels. Green: Set your own green color levels. Blue:Set your own blue color levels.
	Select the screen color. Warm: Set the screen to warm color temperature (more red). Medium: Set the screen to medium color temperature. Cool: Set the screen to cool color temperature (more blue).

Display

- 1 Press MENU button on the bottom of the Monitor set to display the Menu OSD.
- 2 Select the "Next Menu" button to enter the more option settings.
- 3 Select **Display** by pressing the ▶ button.
- 4 Enter to **Display** by pressing the **▼** button.
- 5 Set the options by pressing the ◀ or ▶ or ▼ buttons.
- 6 Select **EXIT** to leave the OSD menu.

 To return to the upper menu or set other menu items, use the up arrow (♠) button.



Each option is explained below.

Menu > Next Menu > Display	Description		
Horizontal	To move image left and right.		
Vertical	To move image up and down.		
Clock	To minimize any vertical bars or stripes visible on the screen background. The horizontal screen size will also change.		
Phase	To adjust the focus of the display. This item allows you to remove any horizontal noise and clear or sharpen the image of characters.		

Audio

- 1 Press MENU button on the bottom of the Monitor set to display the Menu OSD.
- 2 Select the "Next Menu" button to enter the more option settings.
- 3 Select **Audio** by pressing the ▶ button.
- 4 Enter to **Volume** by pressing the **▼** button.
- 5 Set the options by pressing the ◀ or ▶ buttons.
- 6 Select **EXIT** to leave the OSD menu.

 To return to the upper menu or set other menu items, use the up arrow (♠) button.



Menu > Next Menu > Audio	Description
Volume	To adjust the volume of headphone/earphone.(Only for HDMI input)

Others

- 1 Press MENU button on the bottom of the Monitor set to display the Menu OSD.
- 2 Select the "Next Menu" button to enter the more option settings.
- 3 Select **Others** by pressing the **▶** button.
- 4 Enter to **Others** by pressing the **▼** button.
- 5 Set the options by pressing the ◀ or ▶ or ▼ buttons.
- 6 Select **EXIT** to leave the OSD menu.

 To return to the upper menu or set other menu items, use the up arrow (♠) button.



Menu > Next Menu > Others	Description		
Language	To choose the language in which the control names are displayed.		
Power Indicator	Use this function to set the power indicator on the bottom side of the monitor to On or Off.If you set Off, it will go off. If you set On at any time, the power indicator will automatically be turned on.		
Automatic Standby	If you do not press any button on the monitor set for a certain period, the monitor set will automatically switch to standby mode.		

READER Setting

- 1 Press **READER** button on the bottom of the Monitor set to display the Reader Mode OSD.
- 2 Set the options by pressing the ◀ buttons.



Each option is explained below.

Reader Mode	Description
Reader 1	It is a mode that the screen is adjusted to the best for the newspaper. If you want screen more bright, you can control brightness in Menu OSD.
Reader 2	It is a mode that the screen is adjusted to the best for the cartoon. If you want screen more bright, you can control brightness in Menu OSD.
Reader Off	It is a mode that reader mode is off.




If option of Reader Mode is Reader 1 or Reader 2, Picture Mode will automatically be Custom and Super Energy Saving will automatically be Off.

FUNC. Setting

SUPER ENERGY SAVING

- 1 Press **FUNC**. button on the bottom of the Monitor set to display the **FUNC**. OSD.
- 2 Enter to SUPER ENERGY SAVING by pressing the ▼ button.
- 3 Set the options by pressing the ◀ or ▶ or ▼buttons.
- 4 Select **EXIT** to leave the OSD menu. To return to the upper menu or set other menu items, use the up arrow (♠) button.



Each option is explained below.

SUPER ENERGY SAVING	Description	
High	Enables SUPER ENERGY SAVING you can save energy with this energy- high efficient function.	
Low	Enables SUPER ENERGY SAVING you can save energy with this energy-low efficient function.	
Off	Disables SUPER ENERGY SAVING.	



NOTE

- TOTAL POWER REDUCTION: How much power is saved while using the monitor.
- TOTAL CO2 REDUCTION: Change the TOTAL POWER REDUCTION to CO2.
- SAVING DATA(W/h)

	546 mm (21.5 inch)	584 mm (23 inch)	600 mm (23.6 inch)	686 mm (27 inch)
SUPER SAVING(High)	4 W/h	4 W/h	4 W/h	6 W/h
SUPER SAVING(Low)	2 W/h	2 W/h	2 W/h	3 W/h

- Saving Data depends on the Panel. So, those values should be different from each panel and panel vendor. If option of Super Energy Saving is High or Low, monitor luminance become higher or lower depend on source.
- LG calculated these values by using "broadcast video signal" (including broadcast video: IEC 62087)
- SUPER SAVING refers to how much power can be saved using the SUPER ENERGY SAVING function
- If option of Super Energy Saving is High or Low, Picture Mode will automatically be Custom and Reader Mode will automatically be Reader Off.

Picture Mode

- 1 Press FUNC. button on the bottom of the Monitor set to display the **FUNC**. OSD.
- 2 Select **Picture Mode** by pressing the ▶ button.
- 3 Enter to **Picture Mode** by pressing the ▼ button.
- 4 Set the options by pressing the ◀ or ▶ buttons.
- 5 Select **EXIT** to leave the OSD menu. To return to the upper menu or set other menu items, use the up arrow(♠)button.

PC Mode



AV Mode



Each option is explained below.

Picture Mode	Description	
Custom	It is a mode that the user can adjust each element. It can adjust the color mode of the Main Menu.	
Text	It is a mode that the screen is adjusted to the best for the textworks.	
Photo	It is a mode that the screen is adjusted to the best to view pictures.	
Cinema	It is a mode that the screen is adjusted to the best to view the videos.	
Game	It is a mode that the screen is adjusted to the best to play a game.	

Picture Mode	Description	
Custom	It is a mode that the user can adjust each element. It can adjust the color mode of the Main Menu.	
Vivid 1	Adjusts the video image for the retail environment by enhancing the contrast, brightness, Colour, and sharpness.	
Vivid 2		
Standard	Adjusts the image for the normal environment.	
Cinema	It is a mode that the screen is adjusted to the best to view the videos.	



NOTE

If option of Picture Mode is non-Custom, Reader Mode will automatically be Reader Off and Super Energy Saving will automatically be Off.

* Before using below functions, please install DUAL SMART SOLUTION programme.

DUAL DISPLAY

- 1 Press **FUNC.** button on the bottom of the Monitor set to display the **FUNC.** OSD.
- 2 Select DUAL DISPLAY by pressing the ▶ button.
- 3 Enter to **DUAL DISPLAY** by pressing the ▼ button.
- 4 Set the options by pressing the ◀ or ▶ buttons.
- 5 Select **EXIT** to leave the OSD menu. To return to the upper menu or set other menu items, use the up arrow (1) button.




Each option is explained below.

DUAL DISPLAY	Description	
Clone	By selecting Clone, user can use secondary monitor as done mode of primary monitor.	
Extended	By selecting Extended,user can use secondary monitor as extended mode of primar monitor.	
Off	If select Off,DUAL DISPLAY is off.	

^{*} Before using below functions, please install DUAL SMART SOLUTION programme.

DUAL WEB

- 1 Press **FUNC.** button on the bottom of the Monitor set to display the **FUNC.** OSD.
- 2 Select **DUAL WEB** by pressing the ▶ button.
- 3 Enter to **DUAL WEB** by pressing the ▼ button.
- 4 Set the options by pressing the ◀ or ▶ buttons.
- 5 Select **EXIT** to leave the OSD menu.To return to the upper menu or set other menu items, use the up arrow (♠) button.



Each option is explained below.

DUAL WEB Description	
On	Help user to browse web efficiently by dividing in half. Help to arrange and move windowson screen. Help user to control dividedwindows ratio.
Off	If select Off,DUAL WEB is off.



When monitor goes to power saving mode with pc saving option-> Pressing any button -> OSD
appear and user should press dual button -> User can bring back to normal mode.

TROUBLESHOOTING

Check the following before calling for service.

No image appears		
Is the power cord of the display connected?	 Check and see if the power cord is connected properly to the power outlet. 	
Is the power indicator light on?	Press the Power button.	
Is the power on and the power indicator White?	Adjust the brightness and the contrast.	
Is the power indicator flickering?	 If the display is in power saving mode, try moving the mouse or pressing any key on the keyboard to bring up the screen. Try to turn on the PC. 	
Do you see an "OUT OF RANGE" message on the screen?	This message appears when the signal from the PC (video card) is out of horizontal or vertical frequency range of the display. See the 'Specifications' section of this manual and configure your display again.	
Do you see a "NO SIGNAL" message on the screen?	When the monitor is on "No-Signal" in 5 minutes, the monitor goes to DPM mode.	

Do you see a "OSD LOCKED" message on the screen?		
Do you see "OSD LOCKED" when you push MENU button?	 You can secure the current control settings, so that they cannot be inadvertently changed. You can unlock the OSD controls at any time by pushing the MENU button for several seconds: the message "OSD UNLOCKED" will appear. 	

Display image is incorrect		
Display Position is incorrect.	 Press the AUTO button to automatically adjust your display image to the ideal setting. 	
On the screen background, vertical bars or stripes are visible.	 Press the AUTO button to automatically adjust your display image to the ideal setting. 	
Any horizontal noise appearing in any image or characters are not clearly portrayed.	 Press the AUTO button to automatically adjust your display image to the ideal setting. Check Control Panel ➤ Display ➤ Settings and adjust the display to the recommended resolution or adjust the display image to the ideal setting. Set the color setting higher than 24 bits (true color). 	



CAUTION

- Check Control Panel ➤ Display ➤ Settings and see if the frequency or the resolution were changed. If yes, readjust the video card to the recommend resolution.
- · If the recommended resolution (optimal resolution) is not selected, letters may be blurred and the screen may be dimmed, truncated or biased. Make sure to select the recommend resolution.
- · The setting method can differ by computer and O/S (Operation System), and resolution mentioned above may not be supported by the video card performance. In this case, please ask to the computer or the video card manufacturer.

Display image is incorrect	
The screen color is mono or abnormal.	 Check if the signal cable is properly connected and use a screwdriver to fasten if necessary. Make sure the video card is properly inserted in the slot. Set the color setting higher than 24 bits (true color) at Control Panel Settings.
The screen blinks.	 Check if the screen is set to interlace mode and if yes, change it to the recommend resolution.

Do you see an "Unrecognized monitor, Plug&Play (VESA DDC) monitor found" message?		
Have you installed the display driver? Be sure to install the display driver from the display driver CD (or diskette) that comes with your display. Or, you can also download t driver from our web site: http://www.lg.com. Make sure to check if the video card supports Plug&Play function.		

The screen is flickering.		
Did you select the recommended resolution?	 If the selected resolution is HDMI 1080i 60/50 Hz, the screen may be flickering. Change the resolution to the recommended resolution 1080P. 	

22M45HQ

Display	Screen Type	54.6 cm (21.5 inch) Flat Panel Active matrix-TFT LCDAnti- Glare coating
		Visible diagonal size: 54.6 cm
	Pixel Pitch	0.247 mm x 0.247 mm (Pixel Pitch)
Sync Input	Horizontal Frequency	30 kHz to 83 kHz (Automatic)
	Vertical Frequency	56 Hz to 75 Hz (D-SUB) 56 Hz to 61 Hz (HDMI)
	Input Form	Separate Sync. Digital
Video Input	Signal Input	15 pin D-SUB Connector /HDMI Connector
	Input Form	RGB Analog (0.7 Vp-p/ 75 ohm)
Resolution	Max	D-SUB(Analog): 1920 x 1080 @ 60 Hz HDMI (Digital): 1920 x 1080 @ 60 Hz
	Recommend	VESA 1920 x 1080 @ 60 Hz
Plug & Play	DDC 2B(Analog,HDMI)	
Power Consumption	On Mode : 21 W (ENERGY STAR® standard)* Sleep Mode ≤ 0.3 W Off Mode ≤ 0.3 W	
Power Input	19 V 1.2 A	
AC-DC Adapter	Type ADS-40SG-19-3 19025G, manufactured by SHENZHEN HONOR ELECTRONIC or Type ADS-40FSG-19 19025GPG-1, manufactured by SHENZHEN HONOR ELECTRONIC or Type ADS-40FSG-19 19025GPBR-1, manufactured by SHENZHEN HONOR ELECTRONIC or Type ADS-40FSG-19 19025GPI-1, manufactured by SHENZHEN HONOR ELECTRONIC or Type ADS-40FSG-19 19025GPCU-1, manufactured by SHENZHEN HONOR ELECTRONIC or Type ADS-40FSG-19 19025GPB-2, manufactured by SHENZHEN HONOR ELECTRONIC or Type LCAP21, manufactured by LIEN CHANG ELECTRONIC ENTERPRISE or Type LCAP26-A, manufactured by LIEN CHANG ELECTRONIC ENTERPRISE or Type LCAP26-E, manufactured by LIEN CHANG ELECTRONIC ENTERPRISE or Type LCAP26-I, manufactured by LIEN CHANG ELECTRONIC ENTERPRISE or Type LCAP26-B, manufactured by LIEN CHANG ELECTRONIC ENTERPRISE or Type LCAP26-B, manufactured by LG Innotek Co.,Ltd or Type PSAB-L202B, manufactured by LG Innotek Co.,Ltd or Type PSAB-L202C, manufactured by LG Innotek Co.,Ltd or Type PSAB-L202D, manufactured by LG Innotek Co.,Ltd	
Dimensions	With Stand	50.8 cm x 41.7 cm x 18.8 cm
(Width x Height x Depth)	Without Stand	50.8 cm x 31.6 cm x 6.0 cm
Weight	2.6 kg	
Tilt Range	-3° to 20°	
Environmental conditions	Operating Temperature Operating Humidity	10°C to 35 °C 10 % to 80 %
	Storage Temperature Storage Humidity	-20°C to 60 °C 5 % to 90 % non-Condensing
Stand Base	Attached (), Detached (O)	
Power cord	Wall-outlet type	

Product specifications shown above may be changed without prior notice due to upgrade of product functions.

- * The power consumption level can be different by operating condition and monitor setting.
- * The On mode power consumption is measured with ENERGY STAR® test standard.
- * ENERGY STAR® is a US registered mark of the United States Environmental Protection Agency.

23M45HQ

231414311Q			
Display	Screen Type	58.4 cm (23 inch) Flat Panel Active matrix-TFT LCDAnti- Glare coating Visible diagonal size: 58.4 cm	
	Pixel Pitch	0.265 mm x 0.265 mm (Pixel Pitch)	
Sync Input	Horizontal Frequency	30 kHz to 83 kHz (Automatic)	
	Vertical Frequency	56 Hz to 75 Hz (D-SUB) 56 Hz to 61 Hz (HDMI)	
	Input Form	Separate Sync. Digital	
Video Input	Signal Input	15 pin D-SUB Connector /HDMI Connector	
	Input Form	RGB Analog (0.7 Vp-p/ 75 ohm)	
Resolution	Max	D-SUB(Analog) : 1920 x 1080 @ 60 Hz HDMI (Digital) : 1920 x 1080 @ 60 Hz	
	Recommend	VESA 1920 x 1080 @ 60 Hz	
Plug & Play	DDC 2B(Analog,HDMI)		
Power Consumption	On Mode : 21 W (ENERGY STAR® standard)* Sleep Mode ≤ 0.3 W Off Mode ≤ 0.3 W		
Power Input	19 V 1.3 A		
AC-DC Adapter	Type ADS-40SG-19-3 19025G, manufactured by SHENZHEN HONOR ELECTRONIC or Type ADS-40FSG-19 19025GPG-1, manufactured by SHENZHEN HONOR ELECTRONIC or Type ADS-40FSG-19 19025GPBR-1, manufactured by SHENZHEN HONOR ELECTRONIC or Type ADS-40FSG-19 19025GPCU-1, manufactured by SHENZHEN HONOR ELECTRONIC or Type ADS-40FSG-19 19025GPCU-1, manufactured by SHENZHEN HONOR ELECTRONIC or Type ADS-40FSG-19 19025GPB-2, manufactured by SHENZHEN HONOR ELECTRONIC or Type LCAP21, manufactured by LIEN CHANG ELECTRONIC ENTERPRISE or Type LCAP26-A, manufactured by LIEN CHANG ELECTRONIC ENTERPRISE or Type LCAP26-E, manufactured by LIEN CHANG ELECTRONIC ENTERPRISE or Type LCAP26-I, manufactured by LIEN CHANG ELECTRONIC ENTERPRISE or Type LCAP26-B, manufactured by LIEN CHANG ELECTRONIC ENTERPRISE or Type LCAP26-B, manufactured by LIEN CHANG ELECTRONIC ENTERPRISE or Type PSAB-L203A, manufactured by LG Innotek Co.,Ltd or Type PSAB-L202C, manufactured by LG Innotek Co.,Ltd or Type PSAB-L202D, manufactured by LG Innotek Co.,Ltd OTType PSAB-L202D, manufactured by LG Innotek Co.,Ltd		
Dimensions	With Stand	54.4 cm x 40.6 cm x 18.8 cm	
(Width x Height x Depth)	Without Stand	54.4 cm x 33.2 cm x 5.5 cm	
Weight	2.9 kg	2.9 kg	
Tilt Range	-3° to 20°		
Environmental conditions	Operating Temperature Operating Humidity	10°C to 35 °C 10 % to 80 %	
	Storage Temperature Storage Humidity	-20°C to 60 °C 5 % to 90 % non-Condensing	
Stand Base	Attached (), Detached (O)		
Power cord	Wall-outlet type		

Product specifications shown above may be changed without prior notice due to upgrade of product functions.

^{*} The power consumption level can be different by operating condition and monitor setting.

^{*} The On mode power consumption is measured with ENERGY STAR® test standard.

^{*} ENERGY STAR® is a US registered mark of the United States Environmental Protection Agency.

24M45HQ

Display	Carrage Trees	CO C are (22 C inch) Flat Banal Active matrix TET I CDAnti		
Display	Screen Type	60.0 cm (23.6 inch) Flat Panel Active matrix-TFT LCDAnti- Glare coating		
		Visible diagonal size: 60.0 cm		
	Pixel Pitch	0.272 mm x 0.272 mm (Pixel Pitch)		
Sync Input	Horizontal Frequency	30 kHz to 83 kHz (Automatic)		
	Vertical Frequency	56 Hz to 75 Hz (D-SUB) 56 Hz to 61 Hz (HDMI)		
	Input Form	Separate Sync. Digital		
Video Input	Signal Input	15 pin D-SUB Connector /HDMI Connector		
	Input Form	RGB Analog (0.7 Vp-p/ 75 ohm)		
Resolution	Мах	D-SUB(Analog) : 1920 x 1080 @ 60 Hz HDMI (Digital) : 1920 x 1080 @ 60 Hz		
	Recommend	VESA 1920 x 1080 @ 60 Hz		
Plug & Play	DDC 2B(Analog,HDMI)			
Power Consumption	On Mode : 21 W (ENERGY STAR® standard)* Sleep Mode ≤ 0.3 W Off Mode ≤ 0.3 W			
Power Input	19 V 1.3 A			
	Type ADS-40SG-19-3 19025G, manufactured by SHENZHEN HONOR ELECTRONIC or Type ADS-40FSG-19 19025GPG-1, manufactured by SHENZHEN HONOR ELECTRONIC or Type ADS-40FSG-19 19025GPBR-1, manufactured by SHENZHEN HONOR ELECTRONIC or Type ADS-40FSG-19 19025GPL-1, manufactured by SHENZHEN HONOR ELECTRONIC or Type ADS-40FSG-19 19025GPCU-1, manufactured by SHENZHEN HONOR ELECTRONIC or Type ADS-40FSG-19 19025GPB-2, manufactured by SHENZHEN HONOR ELECTRONIC or Type LCAP21, manufactured by LIEN CHANG ELECTRONIC ENTERPRISE or Type LCAP26-A, manufactured by LIEN CHANG ELECTRONIC ENTERPRISE or Type LCAP26-E, manufactured by LIEN CHANG ELECTRONIC ENTERPRISE or Type LCAP26-I, manufactured by LIEN CHANG ELECTRONIC ENTERPRISE or Type LCAP26-B, manufactured by LIEN CHANG ELECTRONIC ENTERPRISE or Type PSAB-L203A, manufactured by LG Innotek Co.,Ltd or Type PSAB-L202B, manufactured by LG Innotek Co.,Ltd or Type PSAB-L202D, manufactured by LG Innotek Co.,Ltd			
Dimensions	With Stand	55.6 cm x 44.5 cm x 18.8 cm		
(Width x Height x Depth)	Without Stand	55.6 cm x 34.4 cm x 5.9 cm		
Weight	3.0 kg			
Tilt Range	-3° to 20°			
Environmental conditions	Operating Temperature Operating Humidity	10°C to 35 °C 10 % to 80 %		
	Storage Temperature Storage Humidity	-20°C to 60 °C 5 % to 90 % non-Condensing		
Stand Base	Attached (), Detached (O)			
	/ titaonea (), Detaonea			

Product specifications shown above may be changed without prior notice due to upgrade of product functions.

^{*} The power consumption level can be different by operating condition and monitor setting.

^{*} The On mode power consumption is measured with ENERGY STAR® test standard.

^{*} ENERGY STAR® is a US registered mark of the United States Environmental Protection Agency.

27M45HQ

Display	Screen Type	68.6 cm (27 inch) Flat Panel Active matrix-TFT LCDAr Glare coating Visible diagonal size: 68.6 cm		
	Pixel Pitch	0.311 mm x 0.311 mm (Pixel Pitch)		
Comp Immort	1 1111111111111111111111111111111111111	, ,		
Sync Input	Horizontal Frequency	30 kHz to 83 kHz (Automatic)		
	Vertical Frequency	56 Hz to 75 Hz (D-SUB) 56 Hz to 61 Hz (HDMI)		
	Input Form	Separate Sync. Digital		
Video Input	Signal Input	15 pin D-SUB Connector /HDMI Connector		
	Input Form	RGB Analog (0.7 Vp-p/ 75 ohm)		
Resolution	Max	D-SUB(Analog) : 1920 x 1080 @ 60 Hz HDMI (Digital) : 1920 x 1080 @ 60 Hz		
	Recommend	VESA 1920 x 1080 @ 60 Hz		
Plug & Play	DDC 2B(Analog,HDMI)			
Power Consumption	On Mode : 27 W (ENERGY STAR® standard) * Sleep Mode ≤ 0.3 W Off Mode ≤ 0.3 W			
Power Input	19 V 1.6 A			
AC-DC Adapter	Type ADS-40SG-19-3 19032G, manufactured by SHENZHEN HONOR ELECTRONIC or ADS-40FSG-19 19032GPG-1, manufactured by SHENZHEN HONOR ELECTRONIC or ADS-40FSG-19 19032GPBR-1, manufactured by SHENZHEN HONOR ELECTRONIC or ADS-40FSG-19 19032GPI-1, manufactured by SHENZHEN HONOR ELECTRONIC or ADS-40FSG-19 19032GPCU-1, manufactured by SHENZHEN HONOR ELECTRONIC OUTPUT: 19 V === 1.7 A			
Dimensions	With Stand	64.1 cm x 48.8 cm x 21.2 cm		
(Width x Height x Depth)	Without Stand	64.1 cm x 39.2 cm x 4.7 cm		
Weight	4.2 kg			
Tilt Range	-5° to 20°			
Environmental conditions	Operating Temperature Operating Humidity	10°C to 35 °C 10 % to 80 %		
	Storage Temperature Storage Humidity	-20°C to 60 °C 5 % to 90 % non-Condensing		
Stand Base	Attached (), Detached (O)			
Power cord	Wall-outlet type			

Product specifications shown above may be changed without prior notice due to upgrade of product

- * The power consumption level can be different by operating condition and monitor setting.
- * The On mode power consumption is measured with ENERGY STAR® test standard.
- * ENERGY STAR® is a US registered mark of the United States Environmental Protection Agency.

Preset Modes (Resolution)

D-SUB Timing

Display Modes (Resolution)	Horizontal Frequency(kHz)	Vertical Frequency(Hz)	Polarity(H/V)	
720 x 400	31.468	70	-/+	
640 x 480	31.469	60	-/-	
640 x 480	37.500	75	-/-	
800 x 600	37.879	60	+/+	
800 x 600	46.875	75	+/+	
1024 x 768	48.363	60	-/-	
1024 x 768	60.023	75	+/+	
1152 x 864	67.500	75	+/+	
1280 x 1024	63.981	60	+/+	
1280 x 1024	79.976	75	+/+	
1680 x 1050	65.290	60	-/+	
1920 x 1080	67.500	60	+/+	Recommend Mode

HDMI Timing


Factory support mode (Preset Mode)	Horizontal Frequency(kHz)	Vertical Frequency(Hz)	НДМІ
480P	31.50	60	0
576P	31.25	50	0
720P	37.50	50	0
720P	45.00	60	0
1080i	28.12	50	0
1080i	33.75	60	0
1080P	56.25	50	0
1080P	67.50	60	O Recommend Mode

Indicator

Mode	LED Color
On Mode	White (Only 15 seconds)
Sleep Mode	Blinking White
Off Mode	Off

PROPER POSTURE

Proper posture for using the Monitor set.





Declaration of Conformity

Trade Name: LG

Model: 22M45HA, 23M45HA, 24M45HA,

27M45HA

Responsible Party: LG Electronics Inc.

Address: 1000 Sylvan Ave. Englewood Cliffs

NJ 07632 U.S.A

TEL: 201-266-2534

Make sure to read the Safety Precautions before using the product.

Keep the Owner's Manual (CD) in an accessible place for future reference.

The model and serial number of the SET is located on the back and one side of the SET. Record it below should you ever need service.

MODEL			
SFRIAI			

ENERGY STAR is a set of power-saving guidelines issued by the U.S.Environmental Protection Agency(EPA).



As an ENERGY STAR Partner LGE U. S. A.,Inc. has determined that this product meets the ENERGY STAR **ENERGY STAR** guidelines for energy efficiency.

^{*}above information is only for USA FCC Regulatory