

OWNER'S MANUAL LG Gaming Monitor (LED MONITOR*)

* LG LED Monitor applies LCD screen with LED backlights.

Please read this manual carefully before operating your set and retain it for future reference.

34GK950F

TABLE OF CONTENTS

LICENSE3
- Supported Drivers and Software4
- Product and Button Description5
How to Use the Joystick Button
- Moving and Lifting the Monitor6
Installing on a Table
Adjusting the Stand Height
Adjusting the Angle
Tidying up Cables
Using the Kensington Lock
Installing the Wall Mount Plate
Installing on the Wall
USING THE MONITOR 15
- Connecting to a PC15
HDMI Connection
DisplayPort Connection
- Connecting AV Devices17
HDMI Connection
- Connecting Peripherals17

USB Cable connection
Connecting Headphone

USER SETTINGS	19
- Activating the Main Menu	19
Main Menu Features	
- User Settings	21
Menu Settings	
TROUBLESHOOTING	32
PRODUCT SPECIFICATION	35
- Factory Support Mode	37

LICENSE

Each model has different licenses. Visit www.lg.com for more information on the license.



The terms HDMI and HDMI High-Definition Multimedia Interface, and the HDMI Logo are trademarks or registered trademarks of HDMI Licensing Administrator, Inc.



The SuperSpeed USB Trident logo is a registered trademark of USB Implementers Forum, Inc.

ASSEMBLING AND PREPARING



- · Always use genuine LG components to ensure safety and product performance.
- The product warranty will not cover damage or injury caused by the use of unauthorized components.
- It is recommend that use the supplied components.
- If you use generic cables not certified by LG, the screen may not display or there may be image noises.



NOTE


- · The components may look different from those illustrated here.
- · Without prior notice, all product information and specifications contained in this manual are subject to change to improve the performance of the product.
- To purchase optional accessories, visit an electronics store or an online shopping site, or contact the retailer from which you purchased the product.
- The power cord provided may differ depending upon the region.

Supported Drivers and Software

You can download and install the latest version from the LGE website (www. la.com).

Drivers and Software	Installation Priority	34GK950F
Monitor Driver	Recommended	0
OnScreen Control	Recommended	0

Product and Button Description



How to Use the Joystick Button

You can easily control the functions of the monitor by pressing the joystick button or moving it left/right with your finger.

Basic Functions

	ø	Power on	Press the joystick button once with your finger to turn on the monitor.
		Power off	Press and hold the joystick button once with your finger to turn off the monitor.
	◄/▶	Volume control	You can control the volume by moving the joystick button left/right.
	▲ /▼	Controls screen brightness	You can control the screen's brightness by moving the joystick button up/down.




• The joystick button is located at the bottom of the monitor.

Moving and Lifting the Monitor

When moving or lifting the monitor, follow these instructions to prevent the monitor from being scratched or damaged and to ensure safe transportation, regardless of its shape or size.

- Place the monitor in the original box or packing material before attempting to move it.
- Before moving or lifting the monitor, disconnect the power cord and all other cables.
- Hold the bottom and side of the monitor frame firmly. Do not hold the panel itself.





- When holding the monitor, the screen should face away from you to prevent it from being scratched.
- When transporting the monitor, do not expose the monitor to shock or excessive vibration.
- When moving the monitor, keep it upright and never turn the monitor on its side or tilt it sideways.




CAUTION

- · Avoid touching the monitor screen as much as possible.
- This may result in damage to the screen or some of the pixels used to create images.




If you use the monitor panel without the stand base, its joystick button may
cause the monitor to become unstable and fall, resulting in damage to the
monitor or human injury. In addition, this may cause the joystick button to
malfunction.




Installing on a Table

1 Lift the monitor and place it on the table in an upright position. Place the monitor at least 100 mm away from the wall to ensure sufficient ventilation.



2 Connect the power adapter to the monitor and then plug the power cord into the wall outlet.



3 Press the joystick button on the bottom of the monitor to turn on the monitor.



 Unplug the power cord before moving or installing the monitor. There is risk of electric shock.

Cautions When Connecting Power Cord



100-240 V ~

- Make sure to use the power cord that is provided in the product package and connect it to a grounded power outlet.
- If you need another power cord, please contact your local dealer or the nearest retail store.

Adjusting the Stand Height

- 1 Place the monitor mounted on the stand base in an upright position.
- 2 Handle the monitor with both hands for safety.

Max. 110.0 mm








 When adjusting the screen height, do not place your hand on the stand body to avoid injury to your fingers.

Adjusting the Angle

- 1 Place the monitor mounted on the stand base in an upright position.
- 2 Adjust the angle of the screen.

The angle of the screen can be adjusted forward or backward from -5° to 15° for a comfortable viewing experience.






• To avoid injury to the fingers when adjusting the screen, do not hold the lower part of the monitor's frame as illustrated below.








• Be careful not to touch or press the screen area when adjusting the angle of the monitor.








Swivel (clockwise 20°) Swivel (counter clockwise 20°)





 The left or right side of the monitor head can be slightly rotated up or down (up to 3°). Adjust the horizontal level of the monitor head.



Tidying up Cables

Arrange the cables using the cable holder as shown in the illustration.






Using the Kensington Lock

The connector for the Kensington security system is located at the bottom of the monitor.

For more information on installation and usage, refer to the Kensington lock owner's manual or visit the website at http://www.kensington.com.

Connect the monitor to a table using the Kensington security system cable.





 The Kensington security system is optional. You can obtain optional accessories from most electronics stores.

Installing the Wall Mount Plate

This monitor meets the specifications for the wall mount plate or other compatible devices.

- 1 Place the screen face down. To protect the monitor panel (screen), cover the surface with a soft cloth or the monitor protection pad included in the product package.
- 2 Remove the four screws tightened on the back of the monitor.
- 3 Place the wall mount plate onto the monitor and align it with the screw holes.
- 4 Tighten the four screws using a screwdriver to fix the plate to the monitor.




NOTE

- The wall mount plate is sold separately.
- For more information on installation, refer to the wall mount plate's installation quide.
- Be careful not to apply too much force while mounting the wall mount plate as it may cause damage to the screen.

Installing on the Wall

Install the monitor at least 100 mm away from the wall and leave about 100 mm of space at each side of the monitor to ensure sufficient ventilation. Detailed installation instructions can be obtained from your local retail store. Alternatively, please refer to the manual for how to install and set up a tilting wall mounting bracket.



To install the monitor to a wall, attach a wall mounting bracket (optional) to the back of the monitor.

Make sure that the wall mounting bracket is securely fixed to the monitor and to the wall.

- 1 If you use screws longer than the standard length, it may damage the inside of the product.
- 2 A non-VESA standard screw may damage the product and cause the monitor to fall. LG Electronics is not liable for any accidents relating to the use of non-standard screws.

Wall Mount (mm)	100 x 100
Standard screw	M4 x L10
Number of screws	4
Wall Mount Plate (Optional)	LSW 149



NOTE


- · Use the screws specified by VESA standards.
- The wall mount kit includes the installation guide and all necessary parts.
- The wall mounting bracket is optional. You can obtain optional accessories from your local dealer.
- The length of the screw may differ for each wall mounting bracket. Be sure to use the proper length.
- For more information, please refer to the user manual for the wall mounting bracket.



CAUTION

- Unplug the power cord before moving or installing the monitor to avoid electric shock.
- Installing the monitor on the ceiling or on a slanted wall may result in the monitor falling off, which could lead to injury. Use an authorized LG wall mount and contact the local dealer or qualified personnel.
- Applying excessive force when tightening screws may cause damage to the monitor. Damage caused in this way will not be covered by the product warranty.

- Use the wall mounting bracket and screws that conform to VESA standards.
 Damage caused by the use or misuse of inappropriate components will not be covered by the product warranty.
- When measured from the back of the monitor, the length of each installed screw must be 8 mm or less.



USING THE MONITOR

 The following instructions are based on the 34GK950F model. Illustrations in this manual may differ from the actual product.

Press the joystick button, go to $\mathbf{Settings} \to \mathbf{Input},$ and then select the input option.



CAUTION

- Do not press the screen for a prolonged time. This may cause image distortion.
- Do not display a still image on the screen for a prolonged time. This may cause image retention. Use a screensaver if possible.



NOTE


- When connecting the power cord to the outlet, use a grounded (3-hole) power strip or a grounded power outlet.
- The monitor may flicker when turned on in an area where the temperature is low. This is normal.
- · Sometimes red, green, or blue spots may appear on the screen. This is normal.

Connecting to a PC

- This monitor supports the *Plug and Play feature.
- * Plug and Play: A feature that allows you to add a device to your computer without having to reconfigure anything or install any manual drivers.

HDMI Connection

Transmits digital video and audio signals from your PC to the monitor. Connect your PC to the monitor using the HDMI cable as shown in the illustration below.




! CAUTION

- Using a DVI to HDMI / DP (DisplayPort) to HDMI cable may cause compatibility issues.
- Use a certified cable with the HDMI logo attached. If you do not use a certified HDMI cable, the screen may not display or a connection error may occur.
- · Recommended HDMI cable types
- High-Speed HDMI®/™ cable
- High-Speed HDMI[®]/™ cable with Ethernet

DisplayPort Connection

Transmits digital video and audio signals from your PC to the monitor. Connect the monitor to your PC using the DisplayPort cable as shown in the illustration below.






 There may be no video or audio output depending on the DP (DisplayPort) version of the PC.

Connecting AV Devices

HDMI Connection

HDMI transmits digital video and audio signals from your AV device to the monitor. Connect your AV device to the monitor using the HDMI cable as shown in the illustration below.





NOTE


- Using a DVI to HDMI / DP (DisplayPort) to HDMI cable may cause compatibility issues.
- Use a certified cable with the HDMI logo attached. If you do not use a certified HDMI cable, the screen may not display or a connection error may occur.
- Recommended HDMI cable types
- High-Speed HDMI®/TM cable
- High-Speed HDMI®/TM cable with Ethernet

Connecting Peripherals

USB Cable connection

The USB port on the product functions as a USB hub.

To use USB 3.0, connect the A-B type USB 3.0 cable of the product to the PC. Peripheral devices connected to the USB IN port can be controlled from the PC. For using the USB downstream port, connect the USB A/B type cable as picture





- Make sure to install the most recent Windows OS service pack before using the product.
- · Peripheral devices are sold separately.
- · A keyboard, mouse, or USB device can be connected to the USB port.






Cautions When Using a USB Device

- A USB device with an automatic recognition program installed, or that uses its own driver, may not be recognized.
- Some USB devices may not be supported or may not work properly.
- It is recommended to use a USB hub or hard disk drive with power supplied.
 (If the power supply is not adequate, the USB device may not be recognized properly.)

Connecting Headphones

Connect peripherals to the monitor via the headphones port. Connect as illustrated.





NOTE

- · Peripheral devices are sold separately.
- If you use angled earphones, it may cause a problem with connecting another external device to the monitor. Therefore, it is recommended to use straight earphones.




 Depending on the audio settings of the PC and external device, headphones and speaker functions may be limited.

USER SETTINGS

Activating the Main Menu

- 1 Press the joystick button on the bottom of the monitor.
- 2 Move the joystick up/down (▲/▼) and left/right (◀/►) to set the options.
- 3 Press the joystick button once more to exit the main menu.



Button		Menu Status	Description
	Main m	enu disabled	Enables the main menu.
	Main menu enabled		Exits the main menu. (Holding down the button to turn off the monitor. You can turn off the monitor this way at any time, including when the OSD is on.)
		Main menu disabled	Adjusts the monitor volume level.
		Main menu enabled	Enters the Input features.
	>	Main menu disabled	Adjusts the monitor volume level.
		Main menu enabled	Enters the Settings feature.
		Main menu disabled	Adjusts the monitor brightness level.
		Main menu enabled	Turns off the monitor.
		Main menu disabled	Adjusts the monitor brightness level.
	•	Main menu enabled	Enters the Game Mode feature.

Main Menu Features



Main Menu	Description		
Input	ts input mode.		
Power Off	irns off the monitor.		
Settings	Configures the screen settings.		
Game Mode	Sets the game mode for gaming.		
Exit	Exits the main menu.		

User Settings

Menu Settings

- 1 To view the settings menu, press the joystick button at the bottom of the monitor and then enter the **Settings**.
- 2 Configure the options by moving the joystick up/down/left/right.
- 3 To return to the upper settings or set other settings items, move the joystick to ◀ or press (憑).
- 4 If you want to exit the settings menu, move the joystick to ◀ until you exit.











Game Mode

Game Adjust

Picture Adjust

Input

General

Se	Settings Description	
Game Mode Changes the game mode to the one optimized for a given feature.		Changes the game mode to the one optimized for a given feature.
Game Adjust	djust Adjusts the 1ms Motion Blur Reduction, Free Sync, Black Stabilizer, Response Time, Cross Hair and Game Reset.	
Picture Adjust		Adjusts the Brightness, Contrast, Sharpness, Gamma, Color Temp, R/G/B, Black Level, DFC and Picture Reset.
Input	Input	Selects the input mode.
Ratio		Adjusts the aspect ratio of the screen.
General		Sets Language, SMART ENERGY SAVING, Power LED, Automatic Standby, HDMI Compatibility Mode, DisplayPort Version, Buzzer, OSD Lock, Information and Reset to Initial Settings.



• Your monitor's OSD (On Screen Display) may differ slightly from that shown in this manual.

Game Mode on SDR(Non-HDR)signal.

Settings > Game Mode		Description
Gamer 1		In this mode, users can customize elements including game-related options.
Gamer 2 FPS RTS	Gamer 2	Gamer 1 and Gamer 2 picture modes allow you to save two sets of customized display settings, including game-related setup options.
	FPS	This mode is optimized for FPS games.It is suitable for very dark FPS games.
	RTS	This mode is optimized for RTS Game.
	Vivid	Optimized the screen for vivid colors.
	Reader	Optimizes the screen for viewing documents. You can brighten the screen in the settings menu.
	HDR Effect	Optimizes the screen for high dynamic range.
	sRGB	A standard RGB color space for the monitor and printer.

Game Mode on HDR signal.

Settings > HDR Game Mode		Description		
	Gamer 1	In this mode, users can customize elements including game-related options.		
	Gamer 2	Gamer 1 and Gamer 2 picture modes allow you to save two sets of customized display settings, including game-related setup options.		
	FPS	This mode is optimized for FPS games.It is suitable for very dark FPS games.		
	RTS	This mode is optimized for RTS Game.		
	Vivid	Optimized the screen for vivid colors.		
HDR Game Mode	Standard	Optimized the screen for HDR standard.		
	 NOTE HDR content may not be operated properly depending on the Windows10 OS setting. Please check the HDR On / Off setti When the HDR function is turned on, the characters or picture quality may be poor according to Graphic card performance. While the HDR function is on, screen flickering or cracking may occur when changing the monitor input or power on/off according performance. For information about whether the graphics card and game support HDR, visit their manufacture's website. 			

Settings > Game Adjust		Description		
	ujust	On	This mode minimizes motion blur in fast-moving videos. To take full advantage of this function, select 3440 x 1440 @ 120Hz/144Hz before enabling 1ms Motion Blur Reduction . This function is available for the following vertical frequency. (120Hz,144Hz)	
Game Adjust	1ms Motion Blur Reduction	Off	Turns 1ms Motion Blur Reduction Mode off.	
			tion blur, brightness is reduced with backlight control. Blur Reduction and FreeSync feature can not used at the same time.	
			is game-optimized. nded to turn off when you are not using the gaming function.	

Game Adjust	FreeSync	Supported Int Supported Gr Supported Ve For more info FreeSync and NOTE	N erface: DisplayPort,HDMI. aphic Card : A graphic card that supports AMD's FreeSync/FreeSync 2 is necessary. rsion : Make sure to update the graphic card to the latest driver. rmation and requirement, refer to AMD website at http://www.amd.com/FreeSync 1ms Motion Blur Reduction cannot be enabled simultaneously. un only be used with the extended mode. (*Supported Interface: DisplayPort)	
		Extended	Enable wider frequency range of FreeSync function than basic mode. The screen may flicker during the game play.	
		Basic	Enable basic frequency range of FreeSync function.	
		Off	FreeSync function off.	
	Black Stabilizer	You can control the black contrast to have better visibility in dark scenes. You can easily distinguish objects on dark game screens.		

	Response Time	Sets a response time for displayed pictures based on the speed of the screen. For a normal environment, it is recommended that you use Fast . For a fast-moving picture, it is recommended that you use Faster . Setting to Faster may cause image sticking.			
		Faster	Sets the response time to faster.		
Carra Adirect		Fast	Sets the response time to fast.		
Game Adjust		Normal	Sets the response time to normal.		
		Off	Does not use the response time improvement feature.		
	Cross Hair	Cross hair provides a mark on the center of the screen for First Person Shooter (FPS) games. Users can select the cross hair that fits their gaming environment among four different cross hairs.			
		When the monitor is off or enters energy saving mode, the cross hair feature is automatically turned off.			
	Game Reset	Returns game to the default settings.			

Settings > Picture Adjust			Description			
	Brightness	Adjusts the brig	Adjusts the brightness of the screen.			
	Contrast	Adjusts the con	Adjusts the contrast of the screen.			
	Sharpness	Adjusts the sha	Adjusts the sharpness of the screen.			
	Gamma	Mode 1, Mode 2, Mode 3	The higher the gamma value, the darker the image becomes. Likewise, the lower the gamma value, the lighter the image becomes.			
		Mode 4	If you do not need to adjust the gamma settings, select Mode 4.			
	Color Temp	Custom	The user can adjust it to red, green, or blue by customization.			
		Warm	Sets the screen color to a reddish tone.			
Picture Adjust		Medium	Sets the screen color to between a red and blue tone.			
		Cool	Sets the screen color to a bluish tone.			
	R/G/B	You can customi	You can customize the picture color using Red , Green , and Blue colors.			
	Black Level	Sets the offset level (for HDMI only). Offset: as a reference for a video signal, this is the darkest color the monitor can display.				
		High	Keeps the current contrast ratio of the screen.			
		Low	Lowers the black levels and raises the white levels from the current contrast ratio of the screen.			
	DFC	On	Adjusts the brightness automatically according to the screen.			
		Off	Disables the DFC feature.			
	Picture Reset	Returns picture and color to the default settings.				

Settings > Input		Description		
	Input	Selects the input mode.		
		Adjusts the aspect ratio of the	e screen.	
		Full Wide	Displays the video in widescreen, regardless of the video signal input.	
		Original	Displays video according to the aspect ratio of the video signal input.	
		Just Scan	The aspect ratio is not adjusted from the original.	
Input		Cinema 1	Enlarges the screen with an aspect ratio of 21:9. (at 1080p)	
	Ratio	Cinema 2	Enlarges the screen with an aspect ratio of 21:9, including the black box at the bottom for subtitles. (at 1080p)	
		x 1440)	ne for Full Wide , Original, and Just Scan options at the recommended resolution. (3440 na 1,Cinema 2 menu on FreeSync Mode. (Go to Picture → Game Adjust → FreeSync , or Extended to Off)	

Settings > General		Description			
	Language	Sets the menu :	screen to the desired language.		
		High	Saves energy using the high-efficiency SMART ENERGY SAVING feature.		
	SMART ENERGY SAVING	Low	Saves energy using the low-efficiency SMART ENERGY SAVING feature.		
	SAVIIVG	Off	Disables the SMART ENERGY SAVING feature.		
		Turns the powe	r LED on the bottom of the monitor on or off.		
			The power LED turns on automatically.		
	Power LED	On	On Mode: Red		
	Power LLD	0	Sleep Mode (Standby Mode): Flashing Red		
			Off Mode: Off		
		Off	The power LED turns off.		
General	Automatic Standby	Feature that automatically turns off the monitor when there is no movement on the screen for a period of time. You can set timer for the auto-off function. (Off, 4H, 6H, and 8H)			
		HDMI Compatibility Mode feature can recognize the legacy equipment that does not support HDMI 2.0.			
	HDMI Compatibility	On	Enables HDMI Compatibility Mode.		
		Off	Disables HDMI Compatibility Mode.		
		NOTE			
	Wode	If the connected device does not support HDMI Compatibility Mode, the screen or sound may not work properly.			
		When HDMI Compatibility Mode is on, 3440 x 1440 @ 100/120/144Hz resolution is not supported.			
		Some older graphics cards do not support HDMI 2.0, but you can select HDMI 2.0 resolution in the control panel of window. This may cause the screen to appear abnormally.			
	DisplayPort Version	DisplayPort version to match the version of the connected external device (1.4,1.2 and 1.1). If you want to use the DP version to 1.4.			

	Buzzer	This feature lets you set the sound generated from Buzzer when your monitor powers on.		
On Enables your monitor's Buzzer . Off Disables your monitor's Buzzer .			Enables your monitor's Buzzer .	
			Disables your monitor's Buzzer .	
	OSD Lock	This feature dis	sables the configuration and adjustment of menus.	
		On	Enables OSD Lock.	
		Disables OSD Lock.		
General		NOTE • All features are disabled except Brightness, Contrast in Picture Adjust, Input, OSD Lock and Information in General		
	Information	The display info	ormation will be shown the Serial Number, Total Power On Time, Resolution, FreeSync certification logo.	
NOTE • The FreeSync certification logo is only shown when the FreeSync option is set to Extended			certification logo is only shown when the FreeSync option is set to Extended.	
	Reset to Initial Settings	Restores the default settings.		

TROUBLESHOOTING

Nothing is displayed on the screen.			
Is the monitor's power cord plugged in?	Check if the power cord is correctly plugged into the power outlet.		
Is the power LED on?	Check the power cable connection and press the power button.		
Is the power on and the power LED displaying red?	Check that the connected input is enabled (Settings > Input).		
Is the power LED blinking?	 If the monitor is in sleep mode, move the mouse, or press any key on the keyboard, to switch the display on. Check if the computer is turned on.		
Is the The screen is not currently set to the recommended resolution. If you have no video or the screen flickers, see the troubleshooting guide in the product owner's manual. message being displayed?	This occurs when signals transferred from the PC (graphics card) are out of the recommended horizontal or vertical frequency range of the monitor. Please see the Product Specification section of this manual to set the appropriate frequency.		
Is the No Signal message being displayed?	This is displayed when the signal cable between the PC and the monitor is missing or disconnected. Check the cable and reconnect it.		
Have you installed the display driver?	Be sure to install the display driver from our web site: http://www.lg.com. Make sure to check if the graphics card supports Plug and Play function.		

Some features are disabled.				
Are some functions not available when you press the Menu button?	The OSD is locked. Go to Settings > General and set OSD Lock to Off .			

The screen	retains	an image
THE SCIECT	I C CUIII 3	an image

Does image sticking occur even when the monitor is turned off?

- Displaying a still image for a prolonged time may cause damage to the screen, resulting in the retention of the image.
- To extend the lifetime of the monitor, use a screensaver.

Screen display is unstable and shaky. / Images displayed on the monitor leave shadow trails.

Did you select the appropriate resolution?

 If the selected resolution is HDMI 1080i 60/50 Hz (interlaced), the screen may be flickering. Change the resolution to 1080p or the recommended resolution.



NOTE

- Vertical Frequency: In order to display an image, the screen must be refreshed dozens of times per second, like a fluorescent lamp. The number of times the screen is refreshed per second is called vertical frequency, or refresh rate, and is represented by Hz.
- Horizontal Frequency: The time it takes to display one horizontal line is called the horizontal cycle. If 1 is divided by the horizontal interval, the result is the number of horizontal lines displayed per second. This is called horizontal frequency and is represented by kHz.
- Check if the graphics card's resolution or frequency is within the range allowed by the monitor and set it to the recommended (optimal) resolution **Control Panel** > **Display** > **Settings** in Windows. (The settings may differ depending on the operating system (OS) you use.)
- Not setting the graphics card to the recommended (optimal) resolution may result in blurred text, a dimmed screen, a truncated display area or misalignment of the display.
- The setting methods may be different depending on the computer or operating system, and some resolutions may not be available depending on the performance of the graphics card. If this is the case, contact the manufacturer of the computer or graphics card for assistance.
- Some graphics cards may not support 3440 x 1440 resolution. If the resolution cannot be displayed, contact the manufacturer of your graphics card.

The display color is abnormal.			
Does the display appear discolored (16 colors)?	• Set the color to 24 bit (true color) or higher. In Windows, go to Control Panel > Display > Settings > Color Quality . (The settings may differ depending on the operating system (OS) you use.)		
Does the display color appear unstable or monochrome?	Check if the signal cable is connected properly. Reconnect the cable or reinsert the PC's graphics card.		
Are there spots on the screen?	When using the monitor, pixilated spots (red, green, blue, white, or black) may appear on the screen. This is normal for an LCD screen. It is not an error, nor is it related to the monitor's performance.		

No sound from the headphone port.				
Are images displayed using DP (DisplayPort) or HDMI input without sound?	 Make sure that the headphone port connections are made properly. Try increasing the volume with the joystick. Set the audio output of the PC to the monitor you are using. On Microsoft Windows, go to Control Panel > Hardware and Sound > Sound > set the Monitor as default device. (The settings may differ depending on the operating system (OS) you use.) 			

PRODUCT SPECIFICATION

LCD Screen	Туре	Туре		TFT (Thin Film Transistor) LCD (Liquid Crystal Display) Screen		
	Color Depth		HDMI	10-bit color is supported.		
			DP (DisplayPort)	10-bit color is supported.		
	Pixel Pitch		0.2325 mm x 0.2325 r	mm		
Resolution	Max Resolution	on	DP:3440 x 1440 @ 14	44Hz HDMI:3440 x 1440 @ 85Hz		
	Recommende	Recommended Resolution		3440 x 1440 @ 60 Hz		
Operating Frequency	HDMI	Horizontal Frequency	30 kHz to 130 kHz			
		Vertical Frequency	60 Hz to 85 Hz			
	DP	Horizontal Frequency	30 kHz to 225 kHz			
		Vertical Frequency	60 Hz to 144 Hz			
Input Connector	H/P ∩, DP (D	isplayPort) IN, USB (SS	1/2, HDMI IN 1/2, USB U	JP (SSC+)		
Power Sources	Power Rating		19 V === 6.0 A			
Power Consumption (Typical)		Operating Mode: 95 W Typ. (Outgoing condition) * Sleep Mode (Standby Mode): ≤ 0.5 W ** Off Mode: ≤ 0.3 W				
AC/DC Adapter		, manufactured by CHICONY (L-19N-3 190140E, manufac 7.37 A				

Environmental Conditions	Operating Conditions	Temperature	0 °C to 40 °C
		Humidity	Less than 80 %
	Storing Conditions	Temperature	-20 °C to 60 °C
		Humidity	Less than 85 %
Dimensions	Monitor Size (Width x Height x Depth)		
	With Stand	819.4 x 572.6 x 286.5 (mm)	
	Without Stand	819.4 x 361.9 x 104 (mm)	
Weight (Without Packaging)	With Stand	7.3 kg	
	Without Stand	5.5 kg	

Specifications are subject to change without notice.

The Power Consumption level can be different by operating condition and monitor setting.

^{*} The On mode power consumption is measured with LGE test standard (Full White pattern , Maximum resolution).

^{**} The monitor goes to the Sleep Mode in a couple of minutes(Max 5 minutes).

Factory Support Mode

(Preset Mode, HDMI/ DisplayPort PC)

Preset Mode	Horizontal Frequency (kHz)	Vertical Frequency (Hz)	Polarity (H/V)	Remarks
640 x 480	31.469	59.94	-/-	
800 x 600	37.879	60.317	+/+	
1024 x 768	48.363	60.0	-/-	
1152 x 864	54.347	60.05	+/+	
1280 x 720	45	60	+/+	
1280 x 1024	63.981	60.02	+/+	
1600 x 900	60.00	60.00	+/+	
1680 x 1050	65.29	59.954	-/+	
1920 x 1080	67.50	60	+/-	
1920 x 1080	83.894	74.973	+/-	
3440 x 1440	43.82	29.99	+/-	HDMI Only
3440 x 1440	73.68	49.99	+/-	
3440 x 1440	88.82	59.97	+/-	
3440 x 1440	113.03	75.05	+/-	*
3440 x 1440	126.14	85.00	+/-	
3440 x 1440	150.97	99.98	+/-	*
3440 x 1440	183	120	+/-	*
3440 x 1440	217.32	143.92	+/-	*

 $[\]star$ When HDMI Compatibility Mode is on, 3440 x 1440 @ 100/120/144Hz resolution is not supported.

^{*} DisplayPort only

HDMI Timing (Video)

	Factory support mode (Preset Mode)	Vertical Frequency (Hz)	Remarks
1	480p	60	
2	576p	50	
3	720p	50/60	
4	1080p	50/60	
5	2160p	24/25/30/50/60	HDMI Compatibility Mode: Off



The model and serial number of the product are located on the back and on one sid	e of
the product.	

Record them below in case you ever need service.

Model	
Serial No.	

To obtain the source code under GPL, LGPL, MPL, and other open source licenses, that is contained in this product, please visit http://opensource.lge.com.ln addition to the source code, all referred license terms, warranty disclaimers and copyright notices are available for download.LG Electronics will also provide open source code to you on CD-ROM for a charge covering the cost of performing such distribution (such as the cost of media, shipping, and handling) upon email request to opensource@lge.com. This offer is valid for three (3) years from the date on which you purchased the product.