



Please read this manual carefully before operating your set and retain it for future reference.

CM8440 (CM8440, CMS8440F, CMS8440W) CM8340 (CM8340, CMS8440F)



www.lg.com

Safety Information



CAUTION RISK OF ELECTRIC SHOCK



CAUTION: TO REDUCE THE RISK OF ELECTRIC SHOCK DO NOT REMOVE COVER (OR BACK) NO USER-SERVICEABLE PARTS INSIDE REFER SERVICING TO QUALIFIED SERVICE PERSONNEL.



This lightning flash with arrowhead symbol within an equilateral triangle is intended to alert the user to the presence of uninsulated dangerous voltage within the product's enclosure that may be of sufficient magnitude to constitute a risk of electric shock to persons.



The exclamation point within an equilateral triangle is intended to alert the user to the presence of important operating and maintenance (servicing) instructions in the literature accompanying the product.

WARNING: TO PREVENT FIRE OR ELECTRIC SHOCK HAZARD, DO NOT EXPOSE THIS PRODUCT TO RAIN OR MOISTURE.

WARNING: Do not install this equipment in a confined space such as a book case or similar unit.

CAUTION: The apparatus should not be exposed to water (dripping or splashing) and no objects filled with liquids, such as vases, should be placed on the apparatus.



CAUTION: This product employs a Laser System. To ensure proper use of this product, please read this owner's manual carefully and retain it for future reference. Shall the unit require maintenance, contact an authorized service center.

Use of controls, adjustments or the performance of procedures other than those specified herein may result in hazardous radiation exposure.

To prevent direct exposure to laser beam, do not try to open the enclosure.

CAUTION: Do not block any ventilation openings. Install in accordance with the manufacturer's instructions.

Slots and openings in the cabinet are provided for ventilation and to ensure reliable operation of the product and to protect it from over heating. The openings shall be never be blocked by placing the product on a bed, sofa, rug or other similar surface. This product should not be placed in a built-in installation such as a bookcase or rack unless proper ventilation is provided or the manufacturer's instruction has been adhered to.

CAUTION concerning the Power Cord

Most appliances recommend they be placed upon a dedicated circuit;

That is, a single outlet circuit which powers only that appliance and has no additional outlets or branch circuits. Check the specification page of this owner's manual to be certain. Do not overload wall outlets. Overloaded wall outlets, loose or damaged wall outlets, extension cords, frayed power cords, or damaged or cracked wire insulation are dangerous. Any of these conditions could result in electric shock or fire. Periodically examine the cord of your appliance, and if its appearance indicates damage or deterioration, unplug it, discontinue use of the appliance, and have the cord replaced with an exact replacement part by an authorized service center. Protect the power cord from physical or mechanical abuse, such as being twisted, kinked, pinched, closed in a door, or walked upon. Pay particular attention to plugs, wall outlets, and the point where the cord exits the appliance. To disconnect power from the mains, pull out the mains cord plug. When installing the product, ensure that the plug is easily accessible.

This device is equipped with a portable battery or accumulator.

Safety way to remove the battery or the battery from the equipment: Remove the old battery or battery pack, follow the steps in reverse order than the assembly. To prevent contamination of the environment and bring on possible threat to human and animal health, the old battery or the battery put it in the appropriate container at designated collection points. Do not dispose of batteries or battery together with other waste. It is recommended that you use local, free reimbursement systems batteries and accumulators. The battery shall not be exposed to excessive heat such as sunshine, fire or the like.

Table of Contents

1 Getting Started

- 2 Safety Information
- 6 Unique Features
- 6 Accessories
- 7 Playable file Requirement
- 7 Music file requirement
- 7 Compatible USB Devices
- 7 USB device requirement
- 8 Remote control
- 9 Front panel
- 11 Rear panel (CM8440)
- 12 Rear panel (CM8340)

2 Connecting

- 13 How to Affix the Ferrite Core
- 13 Affix the Ferrite Core for power cord
- 13 Connecting to speakers
- 15 Optional Equipment Connection
- 15 Antenna Connection
- 15 USB Connection
- 16 AUX IN Connection
- 16 PORT. IN Connection

3 Operating

- 17 Basic Operations
- 17 CD/USB Operations
- 17 Selecting a folder and an MP3/WMA file
- 18 Deleting an MP3/WMA file
- 19 Playback effect
- 19 JUKE BOX Playback (Program play)
- 20 AUTO DJ playback
- 21 Using a Bluetooth wireless technology
- 21 Listening to music stored on the Bluetooth devices
- 22 Using Bluetooth App
- 25 Radio Operations
- 25 Listening to the radio
- 25 Improving poor FM reception
- 25 Presetting the Radio Stations
- 25 Deleting all the saved stations
- 26 Other Operations
- 26 Turn off the sound temporarily
- 26 Displaying file information (ID3 TAG)
- 26 DEMO
- 26 Using Microphone
- 27 Sound adjustment
- 27 Setting the surround mode
- 27 Setting the USER EQ
- 28 Setting the Clock
- 28 Setting the Clock through "LG Bluetooth Remote" App
- 28 Using your player as an alarm clock
- 28 Sleep Timer Setting
- 28 Dimmer
- 28 Auto power down
- 29 Advanced Operations
- 29 Recording to USB

4 Troubleshooting

31 Troubleshooting

5 Appendix

- 32 Trademarks and Licenses
- 33 Specifications
- 34 Speakers specifications
- 35 Maintenance
- 35 Notes on Discs
- 35 Handling the Unit

1

2

3

4

Unique Features

Bluetooth

Listens to music stored on your bluetooth device.

Portable In

Listens to music from your portable device. (MP3, Notebook, etc.)

Playback effects

Listens to music with various sound and playback effects.

USB Direct Recording

Records music to your USB device.


LG Bluetooth Remote


You can control this unit with your Android device via Bluetooth. This unit and your device must be paired for Bluetooth. Visit "Google Android Market (Google Play Store)" or use the QR code shown below to search for "LG Bluetooth Remote" app. For detailed information, refer to page 22-24.



Accessories

Please check and identify the supplied accessories.





Remote comtrol (1)

Batteries (2)





FM Antenna (1)

AM Antenna (1)

Playable file Requirement

Music file requirement

MP3/WMA file compatibility with this unit is limited as follows.

- Sampling frequency: within 32 to 48 kHz (MP3), within 32 to 48 kHz (WMA)
- Bit rate: within 32 to 320 kbps (MP3), 40 to 192 kbps (WMA)
- Maximum files : Under 999
- Maximum folders: Under 99
- File extensions : ".mp3" / ".wma"
- CD-ROM file format: ISO 9660/ JOLIET
- We recommend that you use Easy-CD Creator, which creates an ISO 9660 file system.

The DTS is not supported. In case of DTS audio format, audio is not output.

You have to set the disc format option to [Mastered] in order to make the discs compatible with the LG players when formatting rewritable discs. When setting the option to Live File System, you cannot use it on LG players.

(Mastered/Live File System : Disc format system for Windows Vista)


Compatible USB Devices

- MP3 Player: Flash type MP3 player.
- USB Flash Drive : Devices that support USB2.0 or USB1.1.
- The USB function of this unit does not support all USB devices.


USB device requirement

- Devices which require additional program installation when you have connected it to a computer, are not supported.
- Do not extract the USB device while in operation.
- For a large capacity USB, it may take longer than a few minute to be searched.
- To prevent data loss, back up all data.
- If you use a USB extension cable or USB hub, the USB device is not recognized.
- Using NTFS file system is not supported. (Only FAT(16/32) file system is supported.)
- This unit is not supported when the total number of files is 1,000 or more.
- External HDD, Card readers, Locked devices, or hard type USB devices are not supported.
- USB port of the unit cannot be connected to PC. The unit cannot be used as a storage device.
- Some USB may not work with this unit.

Remote control



Battery Installation



Remove the battery cover on the rear of the Remote Control, and insert two (size AAA) batteries with lacktriangle and lacktriangle matched correctly.

(¹) (Power) : Switches the unit ON

or OFF.

▲ (Open/Close) : Opens and closes the disc tray.

PRESETFOLDER A/V

- Searches for a folder of MP3/ WMA files. When a CD/USB containing MP3/WMA files in several folders is being played, press **PRESET-FOLDER** \(\nabla\)/\(\nabla\) to select the folder you want to play.
- Chooses a preset number for a radio station.

FUNCTION: Selects the function and input source.

MUTE (: Mutes the sound. **VOL** +/-: Adjusts speaker volume.

TUNER/MEMORY:

- Stores radio stations.
- Deletes all the saved stations.

USB REC: USB direct recording.

SLEEP: Sets the system to turn off automatically at a specified time. (Dimmer: The display window will be darkened by half.)

. 2

REPEAT (MENU): Listens to your tracks/files repeatedly or randomly.

TUNING-/+: Selects the radio stations.

Idd/▶► (Skip/Search):

- Skips Fast backward or Forward.
- Searches for a section within a track/file.

■ ENTER:

- Stops playback or recording.
- Cancels DELETE function.

►/II (Play/Pause):

- Starts or pauses playback.
- Selects STEREO/MONO.

SOUND EFFECT: Chooses sound impressions.

AUTO DJ: Selects the AUTO DJ mode. (For more information refer to the page 20)

DELETE:

number

- Deletes MP3/WMA files.

0 to **9** numerical buttons : Selects numbered tracks, files, or preset

INFO: Sees informations about your music. An MP3 file often come with ID3 tag. The tag gives the Title, Artist, Album or Time information.

REGION EQ: Chooses region equalizer.

CLOCK: For setting the clock and checking the time.


ALARM: With the ALARM function you can turn CD, USB play and TUNER reception on at a desired time.

SET: Confirms the setting.

JUKE BOX:

- Selects JUKE BOX mode.
- Makes your favorites list.

Front panel



- 1 ()/ (Power)
- 2 Display window
- 3 Bluetooth

Selects Bluetooth.

◆ 1/2

Selects the USB 1 or USB 2

4 FUNCTION

Selects the function and input source. Turn **FUNCTION** knob clockwise or counterclockwise.

- 5 >/II (Play/Pause)
 - Starts or pauses playback.
 - Selects Stereo/Mono.
- 6 BASS BLAST

Selects the BASS BLAST or BYPASS sound directly.

- **7 I** ≪ (Skip/Search)
 - Searches backward.
 - Skips to the previous track/file.
- 8 LATIN EO

Chooses locally special equalizer.

9 SLEEP

Sets the system to turn off automatically at a specified time.

(Dimmer: The display window will be darkened by half.)

10 USER EQ

Controls sound register.

CLOCK

For setting the clock and checking the time.

11 PORT. IN jack

MIC jack

MIC VOL.



NFC allows you to install and open "LG Bluetooth Remote" app to NFC-enabled phone.

13 FOLDER

Moves to folder and file in selection mode.

14 ENTER

Selects a folder when searching a file.

15 USB 1/2 Port

You can play or record sound files by connecting the USB device.

R USB REC

Records to USB.

- 16 DELETE
 - Deletes MP3/WMA files. (USB only)
 - Deletes a song on JUKE BOX list.

JUKE BOX

- Makes your favourites list.
- Switches on and off JUKE BOX.

17 FILE SEARCH

Selects a folder and a file on CD/USB function.

18 □ (Stop)

Stops playback or cancels DELETE function.

19 AUTO DJ

Selects the AUTO DJ mode. (For more information refer to the page 20)

- 20 >> (Skip/Search)
 - Searches forward.
 - Skips to the next track/file.

21 SOUND EFFECT

Chooses sound impressions.

22 📤 (Open/Close)

Opens and closes the disc tray.

28 ALARM

With the ALARM function you can turn CD, USB play and TUNER reception on at a desired time.


DEMO/SET

- Shows demo.
- Confirms the setting.
- **24** MASTER VOLUME

Adjusts speaker volume.

25 Disc tray

Rear panel (CM8440)



- 1 Cooling fan
- 2 Speakers connector
- 3 AUX IN connectors (L/R)
- 4 ANTENNA (FM, AM)


5 Power cord



(!) Caution -

- Connect the power cord to wall outlet directly if possible. Or when you use an extension cable, it is highly recommended to use an extension cable of 110 V / 15 A or 230 V / 15 A, otherwise the unit may not operate properly because of the lack of power supply.
- Do not overload the extension cord with excessive electrical load.

Rear panel (CM8340)



- 1 Cooling fan
- 2 Speakers connector
- 3 AUX IN connectors (L/R)
- 4 ANTENNA (FM, AM)

5 Power cord



(!) Caution

- Connect the power cord to wall outlet directly if possible. Or when you use an extension cable, it is highly recommended to use an extension cable of 110 V / 15 A or 230 V / 15 A, otherwise the unit may not operate properly because of the lack of power supply.
- Do not overload the extension cord with excessive electrical load.


How to Affix the Ferrite Core

Ferrite core may not be provided depending on each nation's regulations.

Affix the Ferrite Core for power cord


You must affix a ferrite core in order to reduce or eliminate electrical interference.

- 1. Pull the stopper [a] of the ferrite core to open.
- 2. Wind the power cord around the ferrite core twice.
- 3. Close the ferrite core until it clicks.



Connecting to speakers

Connect the speaker cable plugs to the SPEAKERS connector. Make sure to connect the speaker's plug to the corresponding speaker connector when connecting the plug.



CM8440

Color	Speaker	
Grey	SURR.R	
Red	FRONT R	
Orange	SUB WOOFER	
Blue	SURR.L	
White	FRONT L	

CM8340

Color	Speaker
Grey	SURR.R
Red	FRONT R
Blue	SURR.L
White	FRONT L



!\ Caution

- Do not try to lift the speaker alone. It needs two persons to lift the speaker. Otherwise it may result in the speaker malfunction and cause personal injury and/or property damage.
- The speakers must be placed at a distance of about 20 cm from the unit for preventing the vibration caused by the speakers.







20 cm

20 cm

- Check the volume level before playing music to prevent infirm, child, and pregnant women from being shocked by the sudden and loud sound from the unit.
- Do not use the unit in a limited space.
 It may damage a person's hearing. It is recommended to use it in a wide space.
- Be careful to make sure children not to put their hands or any objects into the *speaker duct.
 - *Speaker duct: A hole for plentiful bass sound on speaker cabinet (enclosure).
- The speakers contain magnet parts, so color irregularity may occur on the TV screen or PC monitor screen. Please use the speakers far away from either TV screen or PC monitor.
- Make sure to install the speaker with other people in order to prevent it from falling and causing injuries to the installer.


Optional Equipment Connection

Antenna Connection

Connect the supplied FM/AM antenna for listening to the radio.

Connect the AM loop antenna to the AM antenna connector.


Connect the FM wire antenna to the FM antenna connector.



- Note
- To prevent noise pickup, keep the AM Loop antenna away from the unit and other components.
- Be sure to fully extend the FM wire antenna.

USB Connection

Connect a USB device (or MP3 player, etc.) to the USB ports on the unit.



Note


Removing the USB device from the unit:

- Choose a different function/mode or press ■ ENTER on the remote control or □ on the unit twice in a row.
- 2. Remove the USB device from the unit.

AUX IN Connection


Connect an output of auxiliary device(Camcoder, TV, Player, etc) to the **AUX IN** (L/R) connector.

If your device has only one output for audio(mono), connect it to the left (white) audio jack on the unit.



PORT. IN Connection

Connect an output (earphone or line out) of portable device (MP3 or PMP etc) to the **PORT. IN** connector.



Listening to music from your portable player or external device

The unit can be used to play the music from many types of portable player or external device.

1. Connect the portable player to the PORT. IN connector of the unit.

Or

Connect the external device to the AUX IN connector of the unit.

- 2. Turn the power on by pressing $\bigcirc/1$.
- Select the PORTABLE or AUX function by pressing **FUNCTION** on the remote control or rotating **FUNCTION** knob.
- 4. Turn on the portable player or external device and start it playing.

Basic Operations

CD/USB Operations

- 1. Insert the disc by pressing ♠ or connect the USB device to the USB port.
- 2. Select the CD or USB function by pressing **FUNCTION** on the remote control or by rotating **FUNCTION** knob on the unit.

То	Do this
Stop	Press ENTER on the remote
этор	control or 🗖 on the unit.
Playback	Press ►/II on the remote control
- iay za cir	or >/ on the unit.
Pause	Press ►/II on the remote control or
raase	>/II on the unit during playback.
Searching	Press ► on the remote
for a section	control or I />>I on the unit
within a track/	during playback and release it at
file	the point you want to listen to.
Selecting Press 0 to 9 numerical button.	
a track/file	the remote control to go to the
directly	desired file or track directly.
	During playback,
	(1) By using ► buttons:
	Press I ◀◀/▶▶ I to go to the
Skipping to	next track/file or to return to the
the next/	beginning of the current track/file.
previous	Press I twice briefly to step
track/file	back to the previous track/file.
l dely inc	(2) By using FILE SEARCH knob:
	Rotate FILE SEARCH on the unit
	and press >/II to play the track/
	file.
Dlauring	Press REPEAT(MENU) on the
Playing	remote control repeatedly. Refer
repeatedly or randomly	to the note for details about the
Tariuoitily	display change.

Auto Play

- AUDIO/MP3/WMA CD is played automatically after tray is open & closed.
- Automatically switches to the CD function if tray is open & closed when there is no disc in tray.



Note

• The display changes in the following order.

USB	MP3/WMA CD	AUDIO CD
REPEAT TRK	REPEAT TRK	REPEAT TRK
REPEAT *DIR	REPEAT DIR	-
REPEAT ALL	REPEAT ALL	REPEAT ALL
RANDOM	RANDOM	RANDOM
OFF	OFF	OFF

*DIR: Directory

- When you play JUKE BOX list, only REPEAT TRK and REPEAT ALL are available.
- Even after restarting the unit or switching one function to another, you can listen to music from the point where it's last been played.
- The next file name is displayed every 30 seconds. (Except RANDOM play, AUTO DJ RANDOM play, the last file of playlist, etc.)
- If you leave the disc tray open for 5 minutes, it will close automatically.

Selecting a folder and an MP3/WMA file

On the unit

- 1. Press FOLDER and rotate FILE SEARCH until a desired folder appears.
- 2. Press ENTER and rotate FILE SEARCH until a desired file appears. Press >/II to play it.


On the remote control

- 1. Press **PRESET-FOLDER** Λ/V repeatedly until a desired folder appears.
- 2. Press ►/II to play it. The first file of folder will play.



Note

• CD / USB Folders/Files are recognized as below



- If there is no file in a folder, the folder will not appear.
- Folders will be presented as the following order:

 $ROOT \rightarrow FOLDER 1 \rightarrow FOLDER 3 \rightarrow FOLDER$ 7 → FOLDER 8 → FOLDER 5 → FOLDER 6

- File will be played from lambda file No.1 to lambda file No.14 one by one.
- Files and folders will be presented in order recorded and may be presented differently according to the record circumstances.
- *ROOT: The first screen you can see when a computer recognize the USB is "ROOT".

Deleting an MP3/WMA file

You can delete file, folder or format by pressing **DELETE**. This function is supported only in stop status. (USB only)

- 1. -Select the file you want to delete and press DELETE.
 - -Select the folder you want to delete by pressing **FOLDER** and rotating **FILE SEARCH** and press **DELETE**.
 - -Press and hold **DELETE** to format the USB device

Press **DELETE** repeatedly during selecting the MP3/WMA file

The display changes in the following order.

- DEL EILE? : Deletes file
- DEL FOLDER? : Deletes folder
- FORMAT?: Formats USB
- 2. To delete file/folder or format, press ▶/**II** on the remote control or press >/|| on the unit.
- 3. If you want to exit the current mode, press ■ ENTER on the remote control or press □ on the unit.



Caution -

- Do not extract the USB device during operation. (play, delete, etc.)
- Regular back up is recommended to prevent data loss.
- The delete function may not be supported according to the USB status. (lock, etc.)

Playback effect

The unit supports AUTO DJ and JUKE BOX playback.

JUKE BOX Playback (Program play)

JUKE BOX function enables you to make a playlist of your favourite tracks/files from a disc or USB device. A playlist of up to 100 tracks/files can be entered for each media (CD, USB1,USB2). Possible to save a total of 300 tracks/files

Making JUKE BOX list

It is supported only on stop status.

- Press and hold **JUKE BOX** to enter the edit mode
- 2. Select a track/file by pressing ◄◄/▶ы on the remote control or ▮≪/≫▮ on the unit.
- 3. Press JUKE BOX to save the track/file.
- Repeat steps 2 to 3 to store the other tracks/ files.
 (You can modify the list by pressing PRESET-FOLDER Λ/V to select the JUKE BOX program
- 5. Press JUKE BOX once again.

number.)

To play the JUKE BOX list, press ►/ ■ after you make the list.

Enjoying JUKE BOX

Press JUKE BOX twice on stop status. "JUKE BOX ON" appears on the display window. To play JUKE BOX list, press ▶/II on the remote control or >/II on the unit.

To cancel it, press **JUKE BOX** twice. "JUKE BOX OFF" appears on the display window.

Deleting JUKE BOX list

Deleting function is worked only on the edit mode.

- Press and hold **JUKE BOX** to enter the edit mode.
- Select a song by pressing JUKE BOX repeatedly or by pressing PRESET.FOLDER \(\Lambda/\text{V}\).
- 3. Press **DELETE** while a song is selected.



- To check the status of JUKE BOX, press JUKE BOX once. You can also check it by the word "PROG." on the display window.
- If there is no JUKE BOX list, "JUKE BOX NONE" appears on the display window when you press JUKE BOX.
- JUKE BOX is switched off in the case below.
 - Changing the function to the others.
 - Turning off and on the unit.
 - Operating the numeric buttons on the remote control.
 - Playing a file by using **FOLDER** and **FILE SEARCH** on the unit.
- JUKE BOX list is cleared in the case below.
 - Removing the disc or the USB device.
 - Deleting or recording music files in the USB device.

AUTO DJ playback

Auto DJ blends the end of one song into the beginning of another for seamless playback. It equalizes volume across tracks/files for uninterrupted playback.

Press AUTO DJ on the remote control or unit repeatedly, the display changes as followings. RANDOM (AUTO DJ RANDOM) -> REPEAT ALL (AUTO DJ SEOUENTIAL) -> (AUTO DJ OFF)

Mode	Display Window	Description
OFF	- (AUTO DJ OFF)	-
RANDOM	RANDOM (AUTO DJ RANDOM)	The music is played randomly on this mode.
REPEAT	REPEAT ALL (AUTO DJ SEQUENTIAL)	The music is played repeatedly on this mode.



Note

- It is not supported on the AUTO DJ mode to search for a section within a track/file or to play repeatedly or randomly.
- During AUTO DJ mode, it is not available to press **PRESET-FOLDER** Λ/V on the remote control or FOLDER on the unit.
- If you move to other functions or stop the music using □ on the unit (or ■ ENTER on the remote control) on AUTO DJ mode, AUTO DJ function will be disable.
- AUTO DJ function is not supported in the music file whose length is less than 60 seconds.
- During recording, AUTO DJ function is not available.
- Only AUTO DJ SEQUENTIAL is selected when played JUKE BOX list.

Using a Bluetooth wireless technology

About Bluetooth

Bluetooth® is wireless communication technology for short range connection.

The sound may be interrupted when the connection interfered by the other electronic wave or you connect the bluetooth in the other rooms.

Connecting individual devices under Bluetooth® wireless technology does not incur any charges. A mobile phone with **Bluetooth®** wireless technology can be operated via the Cascade if the connection was made via Bluetooth® wireless technology. Available Devices: Mobile phone, MP3, Laptop, PDA

Bluetooth Profiles

In order to use Bluetooth wireless technology. devices must be able to interpret certain profiles. This unit is compatible with following profile. A2DP (Advanced Audio Distribution Profile)

Listening to music stored on the Bluetooth devices

Before you start the pairing procedure, make sure the Bluetooth feature is turned on in to your Bluetooth device. Refer to your Bluetooth device's user guide. Once a pairing operation is performed, it does not need to be performed again.

- 1. Select the Bluetooth function by using the **FUNCTION** on the remote. **FUNCTION** knob on the unit and Bluetooth button on the unit. "BT READY" appears on the display window.
- 2. Operate the Bluetooth device and perform the pairing operation. When searching for this unit with the Bluetooth device, a list of the devices found may appear in the Bluetooth device display depending on the type of Bluetooth device. Your unit appears as "LG MINI(XX:XX)".



XX:XX means the last four digits of BT address. For example, if your unit has a BT address such as 9C:02:98:4A:**F7:08**, you will see "LG MINI(F7:08)" on your Bluetooth device.

3. Enter the PIN code. PIN code · 0000



Note

Depending on the Bluetooth device type. some device have a different pairing way.

- 4. When this unit is successfully connected with your Bluetooth device, "PAIRED" will appear on the display window and bluetooth indicator will be lit up.
- 5. Listen to music. To play a music stored on your Bluetooth device, refer to your Bluetooth device's user guide.



- Sound from the main set can be distorted if you raise the volume of Bluetooth device up to two-thirds or more.
- · When you use the bluetooth function, adjust the volume of a bluetooth device to a proper level to listen to.



Note

 When using Bluetooth® technology, you have to make a connection between the unit and the bluetooth device as close as possible and keep the distance.
 However it may not work well in the case

However it may not work well in the case below:

- There is a obstacle between the unit and the bluetooth device
- There is a device using same frequency with Bluetooth® technology such as a medical equipment, a microwave or a wireless I AN device.
- You should connect your Bluetooth device to this unit again when you restart it.
- The sound may be interrupted when the connection interfered by the other electronic wave.
- You cannot control the Bluetooth device with this unit.
- Pairing is limited one Bluetooth device per one unit and multi-pairing is not supported.
- Depending on the type of the device, you may not be able to use the Bluetooth function.
- You can enjoy wireless system using phone, MP3, Notebook, etc..
- When not connected the Bluetooth, "BLUETOOTH" and "BT READY" appears on the control panel.
- When someone stands and interrupts communication between Bluetooth device and the player, the connection will be disconnected.
- The more distant between the unit and the bluetooth device, the lower the sound quality becomes.
- When Bluetooth connection is disconnected, connect the bluetooth device to the unit again.

Using Bluetooth App



Note

Only Android OS is available to use "LG Bluetooth Remote" app with this unit.

About "LG Bluetooth Remote" App

"LG Bluetooth Remote" app brings a suite of new features to this unit.

To enjoy more features, you are recommended to download and install free "LG Bluetooth Remote" app.

Install "LG Bluetooth Remote" App

 Install "LG Bluetooth Remote" app through QR code. Use the scanning software to scan the QR code.



- 2. Tap an icon for installation.
- 3. Tap an icon for downloading.



Note -

- Make sure that your Bluetooth device is connected to the Internet.
- Make sure that your Bluetooth device has a scanning software application. If you don't have one, download one from "Google Android Market (Google Play Store)".

Install "LG Bluetooth Remote" App through "Google Android Market (Google Play Store)"

- 1. Tap the "Google Android Market (Google Play Store)" icon.
- 2. In the search bar, type in the "LG Bluetooth Remote" and search it.
- 3. In the search result list, find and tap "LG Bluetooth Remote" to start downloading Bluetooth app.
- 4. Tap an icon for installation.
- 5. Tap an icon for downloading.




Note -

- Make sure that your Bluetooth device is connected to the Internet
- Make sure that your Bluetooth device is equipped with "Google Android Market (Google Play Store)".

Install "LG Bluetooth Remote" App through NFC

NFC (Near Field Communication) allows you to install and open "LG Bluetooth Remote" app to NFCenabled phone.

- 1. Activates the NFC feature of your NFC-enabled phone.
- 2. Turn on the unit.
- 3. Tag the back of your NFC-enabled phone over the unit.



- If "LG Bluetooth Remote" app is not installed on your NFC-enabled phone, the linked screen with "LG Bluetooth Remote" app is displayed.
- If "LG Bluetooth Remote" app is installed on your NFC-enabled phone, "LG Bluetooth Remote" app is activated...



Note

- You must activate the NFC feature of your NFC-enabled phone.
- If your NFC-enabled phone's screen is locked, it will not read the NFC.
- If your smart phone case is plated with chrome, NFC is unavailable. Depending on your case's material or thickness, NFC may not be read well.

Activate Bluetooth with "LG Bluetooth Remote" App

"LG Bluetooth Remote" app helps to connect your bluetooth device to this unit.

- 1. Tap "LG Bluetooth Remote" app icon on the home screen to open "LG Bluetooth Remote" app, and go to the main menu.
- 2. Tap [Setting] and select the unit you want.
- 3. If you want to get more information to operate, tap [Setting] and [Help].



- BT app will be available in the software version as follow:
 - Android O/S: Ver 2.3.3 (or later)
- This unit does not support the multi-pairing. If this unit is already connected with other Bluetooth device, disconnect that device and then try again.
- If you use "LG Bluetooth Remote" app for operation, there would be some differences between "LG Bluetooth Remote" app and the supplied remote control. Use the supplied remote control as necessary.
- Depending on the Bluetooth device, "LG Bluetooth Remote" app may not work.
- The connection you've made may be disconnected if you select other application or change the setting of the connected device via "LG Bluetooth Remote" app. In such a case, please check the connection status.
- After connection of BT app, music may be output from your device. In this case, try connecting procedure again.

Radio Operations

Be sure that both FM and AM aerials are connected. (Refer to the page 15)

Listening to the radio

- 1 Press **FUNCTION** on the remote control or rotate **FUNCTION** knob until FM or AM appears on the display window. The last received station is tuned in.
- 2. Auto tunina:

Press and hold TUNING-/+ on the remote control or $|\langle\langle \rangle\rangle|$ on the unit for about two seconds until the frequency indication starts to change, then release. Scanning stops when the unit tunes in a station.

Manual tuning:

Press TUNING-/+ on the remote control or I≪/≫I on the unit repeatedly.

3. Adjust the volume by rotating volume knob on the unit or by pressing **VOL +/-** on the remote control repeatedly.

Improving poor FM reception

Press ►/II on the remote control or >/II on the unit. This will change the tuner from stereo to mono and usually improve the reception.

Presetting the Radio Stations

You can preset 50 stations for FM and AM.

Before tuning, make sure to turn down the volume.

- 1. Press **FUNCTION** on the remote control or rotating **FUNCTION** knob on the unit until FM or AM appears in the display window.
- 2. Press TUNING-/+ on the remote control or **I**≪/≫**I** on the unit to select a desired frequency.
- 3. Press TUNER/MEMORY. A preset number will blink in the display window.
- 4. Press **PRESET·FOLDER** Λ/V to select the preset number vou want.
- 5. Press TUNER/MEMORY. The station is stored.
- 6. Repeat steps 2 to 5 to store other stations.
- 7. To listen a preset station, press **PRESET-FOLDER** Λ/V or 0 to 9 numerical buttons.

Deleting all the saved stations

- Press and hold TUNER/MEMORY for two seconds.
 - "ERASE ALL?" will flash up on the unit display.
- 2. Press TUNER/MEMORY to erase all the saved radio stations.

Other Operations

Turn off the sound temporarily

Press **MUTE** to mute your unit. You can mute your unit, for example, to answer the telephone, the mute icon "X" is blinked in the display window.

Displaying file information (ID3 TAG)

While playing an MP3 file containing file information, you can display the information by pressing INFO.

DEMO

In the power off state, it demonstrates the function on display window with a demo sound and a display by pressing **DEMO/SET**. To cancel the DEMO, press it again.



Note

- While DEMO, this unit will keep DEMO status even if you unplug the power cord connection.
- You can enjoy other functions during the DEMO. Then the DEMO will pause to temporary.
 - Without input key in 10 sec, the DEMO will play back automatically.

Using Microphone

It is available on the function as follows: CD, USB, ALIX-MIC and BLUFTOOTH

- 1. Connect your microphone to the MIC jack.
- 2. Play the music you want.
- 3. Sing along with the accompaniment. Adjust the microphone volume by rotating MIC VOL. clockwise or unclockwise on the unit.



Note

- When not using the microphone, set the MIC VOL. to minimum or turn off the MIC and remove the microphone from the MIC jack.
- If the microphone is set too near the speaker, a howling sound may be produced. In this case, move the microphone away from the speaker or decrease the sound level by using the MIC VOL.
- If sound through the microphone is extremely loud, it may be distorted. In this case, rotate MIC VOL. to minimum.
- AUX-MIC function enables only your voice to output.

Sound adjustment

Setting the surround mode

This system has a number of pre-set surround sound fields. You can select a sound mode you want by using **SOUND EFFECT**.

The displayed items for the Equalizer may be different depending on sound sources and effects.

On Display	Description	
NATURAL	You can enjoy comfortable and natural sound.	
Local Specialization equalizer (Optional)	Regionally optimized sound effect. (FORRO/FUNK/ SERTANEJO/DANGDUT/ARABIC/ PERSIAN/INDIA/REGUETON/ MERENGUE/SALSA/SAMBA/ CUMBIA/AFRO)	
AUTO EQ	Realizes the sound equalizer that is the most similar to the genre of which is included in the MP3 ID3 tag of song files.	
POP CLASSIC JAZZ ROCK	This program lends an enthusiastic atmosphere to the sound, giving you the feeling you are at an actual rock, pop, jazz or classic concert.	
MP3- OPTIMIZER	This function is optimized for compressible MP3 file. It improves the treble sound.	
BASS BLAST	Reinforces the treble, bass and surround sound effect.	
LOUDNESS	Improves the bass and treble sound.	
FOOTBALL	You can enjoy the sound effect FOOTBALL STADIUM.	
BYPASS	You can enjoy the sound without equalizer effect.	

Note

- On some speakers, sound may not be heard or heard in low sound depending on the sound mode.
- Maybe you need to reset the surround mode, after switching the input, sometimes even after the sound track/file changed.
- By pressing BASS BLAST on the unit you can directly select the BYPASS or BASS BLAST sound.
- By rotating **LATIN EQ** on the unit, you can directly select various latin equalizers.

Setting the USER EQ

You can listen to music with equalizer by adjusting the sound level yourself.

- 1. Press **USER EQ** on the unit. "USER EQ" is displayed.
- 2. Press **I** ≪ on the unit while "USER EQ" is displayed.
- 3. Select BASS, MIDDLE, or TREBLE by using **BASS BLAST** on the unit.
- 4. Adjust the sound level by turning Latin EQ knob.
- 5. To finish the setting, press **I** ≪ on the unit..

Setting the Clock

- 1 Turn the unit on
- Press and hold CLOCK.
- 3. Select time mode by pressing ► on the remote control or $|\langle\langle\rangle\rangle|$ on the unit.
 - AM 12:00 (for an AM and PM display) or 0:00 (for a 24 hour display)
- 4. Press **SET** to confirm your selection.
- 5. Select the hours by pressing ► on the remote contro or $|\langle\langle\rangle\rangle$ on the unit.
- 6. Press SET
- 7. Select the minutes by pressing ► on the remote control or $|\langle\langle\rangle\rangle$ on the unit.
- 8. Press SET.

Setting the Clock through "LG Bluetooth Remote" App

Install "LG Bluetooth Remote" app on your Android device. (see page 22 - 24)

Your unit's clock will be automatically synchronized with your device by activating Bluetooth connection through "LG Bluetooth Remote" app.

Using your player as an alarm clock

- 1 Turn the unit on
- 2 Press and hold ALARM
- 3. Press ► on the remote control or |<>/>>| on the unit to change the hours and minutes and press SET to save.
- 4. Press ► on the remote control or ✓ />> on the unit to select function and press **SET** to save
- 5. Press ► on the remote control or I≪/≫I on the unit to change the volume and press **SET** to save. The clock icon "()" shows that the alarm is set.



Note

- If you set the clock time, you can check the time by pressing **CLOCK** even when the player is turned off.
- If you set the clock time and alarm, you can check the alarm icon "O" by pressing **CLOCK** even when the player is turned off.
- If you set the clock time and alarm, you can check the alarm icon "(-)" and setting information by pressing **ALARM** even when the unit is turned off.
- Press **ALARM**, you can selects a **ALARM** on / off mode.

Sleep Timer Setting

Press **SLEEP** repeatedly to select delay time between 10 and 180 minutes. After the delay time, the unit will be turned off.

To cancel the sleep function, press **SLEEP** repeatedly until "SLEEP 10" appears, and then press **SLEEP** once again while "SLEEP 10" is displayed.



Note -

- You can check the remaining time before the unit is turned off.
- Press **SLEEP**. The remaining time appears in the display window.

Dimmer

Press **SLEEP** once. The display window will be darkened by half. To cancel it, press SLEEP repeatedly until dim off.

Auto power down

This unit will turn off itself to save electric consumption in the case were main unit is not connected to external device and is not used for 20

So does this unit after six hours since Main unit has been connected to other device using analogue

Advanced Operations

Recording to USB

You can record a various sound source to USB. (CD, USB, AUX, AUX-MIC, PORTABLE, FM, AM)

- 1. Connect the USB device to the unit.
- Select a function in which you want to record by using **FUNCTION** on the remote control or **FUNCTION** knob on the unit.

One track/file recording - You can record to USB after playing a track/file you want.

All tracks/files recording - You can record to USB after stop.

JUKE BOX list recording - After showing the JUKE BOX list, you can record it to USB. (Refer to the page 19)

- 3. Press **USB REC** on the remote control or **R USB REC** on the unit.
 - If you connect both **USB1** and **USB2**, press **>/II** to record to **USB1** or press □ to record to **USB2**.
- 4. To stop recording, press ☐ on the unit or ENTER on the remote control.

Pausing recording

During recording, press ►/II on the remote control or ►/II on the unit to pause recording. Press it again to restart recording.

(TUNER/AUX/AUX-MIC/PORTABLE only)



Note

- You can control recorded MIC sound according to MIC volume when you record in AUDIO CD X1 speed REC.
- Depending on the sound recording in MIC Input when you record in AUX-MIC Function. (No matter the MIC volume control.)

To select recording bit rate and speed

- Press USB REC on the remote control or USB REC on the unit for longer than 3 seconds.
- 2. Press ► on the remote control or ► on the unit to select a bit rate.
- Press USB REC on the remote control or USB REC on the unit again to select the recording speed.
- Press I◀/▶▶I on the remote control or I≪/≫I on the unit to select a desired recording speed. (AUDIO CD only)

X1 SPEED

- You can listen to music while recording it.

X2 SPEED

- You can just record the music file.
- 5. Press **USB REC** on the remote control or **PS USB REC** on the unit to finish the setting.

Dubbing USB to USB

You can do dubbing a various sound source in **USB1** to **USB2** on USB function.

- Connect a USB device including desired sound files to USB1.
- 2. Connect another USB device to USB2.
- 3. Press **USB REC** on the remote control or **R USB REC** on the unit.
- 4. To stop recording, press ENTER on the remote control or □ on the unit.



Note

- It is not supported to record music stored on bluetooth device.
- You can check the recording percentage rate for the USB record on the display window during the recording. (MP3/WMA CD Only)
- During recording MP3/WMA, there is no sound
- For stable recording, the output sound level goes down on its own when you record music from CD to USB.
- You can only change volume level between MIN and 10 during recording. It will be kept even after recording. (CD Only)
- When you stop recording during playback, the file that has been recorded at that time will be stored. (Except MP3/WMA files)
- Do not remove the USB device or turn off the unit during USB recording. If does not, an incomplete file may be made and not deleted on PC.
- If USB recording does not work, the message like "NO USB", "ERROR", "USB FULL" or "NO REC" is displayed on the display window
- Multi card reader device or External HDD can not be used for USB recording.
- A file is recorded by about 512 Mbyte when you record for a long term.
- Sound of MIC is recorded only during AUDIO CD X1 speed REC. It is recorded AUDIO CD source too
- You can not record in AUTO DJ mode.
- You may not store more than 999 files.



Note -

It'll be stored as follows.

AUDIO CD	MP3/WMA
CD_REC -TRACK_001 -TRACK_002	FILE_REC - ABC(File name) - DEF(File name)
The other source*	TUNER
OTHERS _REC - AUDIO_001 - AUDIO_002	TUNER_REC - AUDIO _001 _ 87-5 FM - AUDIO _002 _ 520 AM

*: AUX, PORTABLE and the like.

TUNER: The current recording frequency is shown.

The making of unauthorized copies of copyprotected material, including computer programs, files, broadcasts and sound recordings, may be an infringement of copyrights and constitute a criminal offense. This equipment should not be used for such purposes.

Be responsible Respect copyrights

Troubleshooting

Problem	Cause & Solution	
No Power.	 The power cord is not plugged in. Plug in the power cord. Check whether electricity failed. Check the condition by operating other electronic devices. 	
No sound.	Check whether you select right function. Press FUNCTION and check the selected function. If not, connect speaker cables correctly. Speaker cables connected correctly.	
The unit does not start playback.	 An unplayable disc is inserted. Check the playable disc. No disc is inserted. Insert a disc. The disc is dirty. Clean the disc. (Refer to the page 35) The disc is inserted upside down. Place the disc with the label or printed side facing upwards. 	
Radio stations cannot be tuned in properly.	 The antenna is positioned or connected poorly. Connect the antenna securely. The signal strength of the radio station is too weak. Tune to the station manually. No stations have been preset or preset stations have been cleared (when tuning by scanning preset channels). Preset some radio stations, see page 25 for details. 	
The remote control does not work properly.		

Trademarks and Licenses

Bluetooth°

Bluetooth® wireless technology is a system which allows radio contact between electronic devices.

Connecting individual devices under Bluetooth® wireless technology does not incur any charges. A mobile phone with *Bluetooth*® wireless technology can be operated via the Cascade if the connection was made via *Bluetooth* * wireless technology.

The *Bluetooth*® word mark and logos are owned by the Bluetooth® SIG, Inc. and any use of such marks by LG Electronics is under license.

Other trademarks and trade names are those of their respective owners.

Specifications

General		
Model	CM8440	CM8340
Power requirements	Refer to the main label.	
Power consumption	Refer to the main label.	
Dimensions (W x H x D)	(290 x 349 x 370) mm	
Net Weight (Approx.)	5.9 kg	
Operating temperature	5 °C to 35 °C (41 °F to 95 °F)	
Operating humidity	60 %	
Bus Power Supply	5 V === 500 mA	

Inputs	
AUX IN	2.0 Vrms (1 kHz, 0 dB), 600 Ω, RCA jack (L, R)
Port In	1.2 Vrms (3.5 mm stereo jack)
MIC	20 mV

Tuner	
FM Tuning Range	87.5 to 108.0 MHz or 87.50 to 108.00 MHz
AM Tuning Range	522 to 1,620 kHz, 520 to 1,710 kHz or 522 to 1,710 kHz

Amplifier		
Model	CM8440	CM8340
Total	1,900 W	1,520 W
Streo mode	380 W x 4	380 W x 4
Sub-woofer	380 W	-

CD	
Frequency Response	40 to 20,000 Hz
Signal-to-noise ratio	75 dB
Dynamic range	80 dB

Speakers specifications

Front speaker		
Туре	2 Way 2 Speaker	
Impedance	6Ω	
Rated Input Power	380 W	
Max. Input power	760 W	
Surround speaker		
Туре	1 Way 1 speaker	
Impedance	6Ω	
Rated Input Power	380 W	
Max. Input power	760 W	
Net Dimensions (W x H x D)	(335 x 445 x 300) mm	
Net Weight	8.8 kg	

Subwoofer (CM8440)		
Туре	1 Way 1 speaker	
Impedance	6 Ω	
Rated Input Power	380 W	
Max. Input power	760 W	
Net Dimensions (W x H x D)	(332 x 455 x 280) mm	
Net Weight	9.8 kg	

• Design and specifications are subject to change without notice.

Maintenance

Notes on Discs

Handling Discs

Never stick paper or tape on the disc.

Storing Discs

After playing, store the disc in its case. Do not expose the disc to direct sunlight or sources of heat and never leave it in a parked car exposed to direct sunlight.

Cleaning Discs

Fingerprints and dust on the disc can cause poor picture quality and sound distortion. Before playing, clean the disc with a clean cloth. Wipe the disc from the center to out.

Do not use strong solvents such as alcohol, benzine, thinner, commercially available cleaners, or anti-static spray intended for old vinyl records.

Handling the Unit

When shipping the unit

Please save the original shipping carton and packing materials. If you need to ship the unit, for maximum protection, re-pack the unit as it was originally packed at the factory.

Keeping the exterior surfaces clean

Do not use volatile liquids such as insecticide spray near the unit. Wiping with strong pressure may damage the surface. Do not leave rubber or plastic products in contact with the unit for a long period of time

Cleaning the unit

To clean the player, use a soft, dry cloth. If the surfaces are extremely dirty, use a soft cloth lightly moistened with a mild detergent solution. Do not use strong solvents such as alcohol, benzine, or thinner, as these might damage the surface of the unit

Maintaining the Unit

The unit is a high-tech, precision device. If the optical pick-up lens and disc drive parts are dirty or worn, the picture quality could be diminished. For details, please contact your nearest authorized service center.

