# Uputstvo za nadogradnju softvera

## Napomena

- 1. Provjerite točnost pune oznake modela TV uređaja
- Npr) 47LX9500-UA: Puna oznaka modela mora imati "-UA".
- Provjerite aplikaciju pune oznake modela i svrhu nadogradnje softvera i kliknite na ime softvera na web stranici
- 3. Ne isključujte TV kabel tokom nadogradnje softvera

## 1. Metoda verifikacije pune oznake modela TV uređaja

Metoda ①. Provjerite naljepnicu TV uređaja(sa strane ili iza)



ili



3) Izaberite "Proizvod/

Software Update
 Picture Test
 Sound Test

Product/Service Info

Close

Network Test

"Servisne informacije"

Metoda 2. Provjerite Menu

- 1) Pritisnite tipku [MENU] na daljinskom upravljaču
- 2) Pritisnite (Crveno) na daljinskom upravljaču.



Metoda<sup>3</sup>. Provjerite Podešavanje.

- 1) Pritisnite [Home] tipku na daljinskom upravljaču.
- 2) Odaberite "Podešavanje".



,	"Servisne informa	cije"
?	SUPPORT SEE	-
	-Software Update -Picture Test -Sound Test	
	Product/Service Info	
3 11 E	Initialization of Premium	수있는

3) Prijeđite na"Podrška"

4) Odaberite "Proizvod/





## 5) Provjerite "Model/Tip"



- 2. Metoda verifikacije pune oznake modela TV uređaja i svrha nadogradnje softvera na web stranici
  - 1 Kliknite na "Upravljački programi i softver".
  - Kliknite na ime softvera



③ Provjerite punu oznaku modela (Npr. 47LX9500-UA) i svrhu nadogradnje softvera

Life's Cond	Podrška za proizvod 47LX9500
Sell press	Televiput/Autor(Odm) Televiput)
romine.	
Register die personal Andrikk zu erotenal Cerks andre bere arterier	Instal Long publication (Agriculture) (C.
falste oprige augeneten Aussieht gen kurborike sonrtise	Annual of Annual Statement (Statement Statement Statement)
mp provid for the to-with the first	tangent a structure all costs and the same compared to the structure of the same sector o
	Nex Just
	Feyniauti an The Intel Research the eff. (2021)
	Technol, Stream, Nr., 45.18 (194)
	Selected (September 2019)
	To start Research for to opposite

#### Traženje softvera.

① Odaberite Vašu zemlju nakon konekcije na <u>www.lq.com</u> . ② Idite na "Podrška".



Svi LG protzvodi ۹
<ul> <li>Televizori/Audio/Video</li> <li>Mobilni telefoni</li> <li>Kućanski aparati</li> <li>IT proizvodi</li> <li>Klima-uređaj/Grijanje</li> <li>Poslovna rješenja</li> </ul>
O LG-u
Podrška Spora Internet veza

#### Kuhajte zdravije,

LG MJ3280 - Konvekc

Grijač na Ugljen poboljšava aps standardním, zbog toga će Vaša

Mikrovalne pećnice 🕨



#### ③ Popunite oznaku modela (Npr. 47LX9500(Popunite ime modela osim "-UA".)

(4) Kliknite "Nastavi".

8



#### (5) Kliknite ime modela

LG Life's Good Svi LG proizvodi Q

#### 0 PODRŠKA

Registriraj te proizvod Podrška za proizvod Često postavljana pitanja Ostale opcije popravka

Kontaktirajte korisničku podršku

Moji proizvodi Podrška za mobilnetelefone

# Pronađite svoj proizvod unosom naziva ili broja modela, odr Unesite naziv ili broj modela Naziv/broj modela 47LX9500 Unesite cijelo ili djelomično ime ili broj. Rezultati 47LX9500 Televizori/Audio/Video 47LX9500 Televizori lli pritisnite vrstu proizvoda

Podrška za proizvod



(8) Kliknite puno ime modela (Npr. 47LX9500-UA)

i svrhu nadogradnje softvera.

Televizori/Audio/Video Televizori <u>Video</u> HIFI sustavi

6 Kliknite "Upravljački programi i softver".

## (7) Kliknite ime softvera.

LG Life's Good		<sup>Traži drugi model</sup> ≻ Podrška za	proizvod 47LX	Set 16 pretavod	Trail drugt model > Podrška za	proizvod 47LX9500	Qvdje smo kaki bismo vam pon
Svi LG proizvodi Q PODRŠKA Registriajte proizvod Cesta postavljana pitanja Ostale opcije popravka Kontaktirajte korisničku podršku Moji proizvodi Podrška za mobilnetelefone	<	Priručnici i dokumenti Upra Priručnici i dokumenti Upra određene model. Svi model korizničkom priručniku. Operacijski sustav (Sve doz The latest firmware file	Televizori/Audio/Video: Telev 47LX9500 Specifikacije, galerija fotografija, recenzij mformacije o proizvodima potražite na <u>Fre</u> Irmate li ovaj proizvod? Registri mate li ovaj proizvod? Registri informacije o janstvu ju ažuriranja upravljeških programa i program e podržavaju nadogradnje sottvera za preuze tupn v v03.20.25	Process     Region of protocol     Region as protocol     Region as a protocol     Cristia postopolica paragena     Cristia postopolica     Region as a multi buestinistica     Region as a multi buestinistica	Model (allower)       Weight of the second sec	PTL/MODE         Bartharton, experimental in entrange increases in entrance         Bartharton, experimental international internatione internatinternatintereational internatione internatinternatinte	Entrance of the second
		Operacijski sustav Windows 2000 Windows NT Windows 98 Windows 95 Windows 3.1	Naziv datoteke The Jatest, firmware file v03.20.25.zip Software Upgrade Guide v1 English.ppt		Preszmi dototeku V vestőlines 2,20-te Oberesztek senteleső, i vesteke vésteke 7, i ker CV , fül	Produce 2020, Velodaia NC, Velodaia NC, Velodaia S. F., Velodaia S. Velodaia NC (Alexan), Velodaia S. F., Velodaia NC (Scherk, Velodaia Vita),	

## Preuzimanje softvera na USB memoriju

① Kliknite na "Preuzmi datoteku" preko web stranice i snimite na Vaše računalo.



- 2 Otpakirajte softver fajl.
- ③ Ubacite USB memoriju u USB ulaz računala.
- ④ Napravite folder u USB memorijskom uređaju. Ime foldera mora biti "LG\_DTV".
- 5 Snimite softver fajl "LG\_DTV" iz foldera sa USB memorije.



## Ubacite USB memoriju u USB ulaz Vašeg TV uređaja.

📰 Pozicija USB ulaza: Sa strane ili iza



USB IN Service (	4 DNLY	
HDM	2	
HDM / DVIIN	1	

#### Pokretanje nadogradnje softvera.

① Ukoliko se pojavi poruka na TV ekranu, molimo odaberite "Start".



- W Ukoliko je ista ili starija verzija softvera na USB memoriji od verzije softvera u TV-u, onda se poruka neće pojaviti.
- ※ Neki USB memorijski uređaji možda neće biti kompatibilni sa Vašim TV aparatom.

U tom slučaju koristite drugi USB uređaj.

2 Ukoliko se izvršava nadogradnja softvera, u donjem delu ekrana TV-a će se pojaviti poruka.



- Kopiranje nove verzije softvera sa USB memorije na TV sistemsku memoriju.
   Ne uklanjajte USB memoriju dok je ova poruka prikazana.
   Ne isključujte TV kabl dok je ova poruka prikazana.
- 2) U toku je nadogradnja softvera. **\* Ne isključujte TV kabl dok je ova poruka prikazana.**
- 3) Ukoliko je nadogradnja gotova, ova poruka je prikazana.
  - I Vaš TV će se automatski restartati za 5 sekundi.